

## **OsmoMSC VTY Reference**

Copyright © 2017

This work is copyright by sysmocom - s.f.m.c. GmbH. All rights reserved.

**COLLABORATORS**

	<i>TITLE :</i> OsmoMSC VTY Reference		
<i>ACTION</i>	<i>NAME</i>	<i>DATE</i>	<i>SIGNATURE</i>
WRITTEN BY		November 3, 2022	

**REVISION HISTORY**

NUMBER	DATE	DESCRIPTION	NAME
v1	18th September 2017	Initial	nh

# Contents

<b>1</b>	<b>VTY reference</b>	<b>1</b>
1.1	Common Commands	1
1.1.1	end	2
1.1.2	exit	2
1.1.3	help	2
1.1.4	list [with-flags]	2
1.1.5	show running-config	3
1.1.6	show vty-attributes	3
1.1.7	show vty-attributes (application library global)	3
1.1.8	write	4
1.1.9	write file [PATH]	4
1.1.10	write memory	4
1.1.11	write terminal	5
1.2	view	5
1.2.1	enable [expert-mode]	5
1.2.2	logging color (0 1)	5
1.2.3	logging disable	6
1.2.4	logging enable	6
1.2.5	logging filter all (0 1)	6
1.2.6	logging filter imsi IMSI	7
1.2.7	logging level (rlllclmmllrrlmncclpaglmsclmgcplholdblreflctrlsmpplranaplvrluics...	7
1.2.8	logging level force-all (debug info notice error fatal)	10
1.2.9	logging level set-all (debug info notice error fatal)	11
1.2.10	logging print category (0 1)	11
1.2.11	logging print category-hex (0 1)	12
1.2.12	logging print extended-timestamp (0 1)	12
1.2.13	logging print file (0 1 basename) [last]	13
1.2.14	logging print level (0 1)	13
1.2.15	logging print thread-id (0 1)	14
1.2.16	logging set-log-mask MASK	14

1.2.17	logging timestamp (0 1)	15
1.2.18	logp (rlllclmmlrrlmncc paglmsclmgcplholdblreflctrl smpp ranapl v rl u cs b ss ap sg...	15
1.2.19	no logging level force-all	18
1.2.20	show alarms	18
1.2.21	show asciidoc counters	19
1.2.22	show bsc	19
1.2.23	show connection [trans]	19
1.2.24	show cpu-sched threads	20
1.2.25	show cs7 (sualm3ualipa) [<0-65534>]	20
1.2.26	show cs7 config	21
1.2.27	show cs7 instance <0-15> as (active all m3ualsua)	21
1.2.28	show cs7 instance <0-15> asp	22
1.2.29	show cs7 instance <0-15> route	22
1.2.30	show cs7 instance <0-15> sccp addressbook	23
1.2.31	show cs7 instance <0-15> sccp connections	23
1.2.32	show cs7 instance <0-15> sccp ssn <0-65535>	24
1.2.33	show cs7 instance <0-15> sccp timers	24
1.2.34	show cs7 instance <0-15> sccp users	25
1.2.35	show cs7 instance <0-15> users	25
1.2.36	show fsm NAME	26
1.2.37	show fsm all	26
1.2.38	show fsm-instances NAME	26
1.2.39	show fsm-instances all	27
1.2.40	show history	27
1.2.41	show logging vty	27
1.2.42	show mgw-pool	28
1.2.43	show neighbor	28
1.2.44	show neighbor (aliu)	28
1.2.45	show neighbor (aliu) (ran-pclmsc-ipa-name) RAN_PC_OR_MSC_IPA_NAME	29
1.2.46	show neighbor (aliu) cgi <0-999> <0-999> <0-65535> <0-65535>	29
1.2.47	show neighbor (aliu) lac <0-65535>	30
1.2.48	show neighbor (aliu) lac-ci <0-65535> <0-65535>	30
1.2.49	show neighbor cgi <0-999> <0-999> <0-65535> <0-65535>	31
1.2.50	show neighbor lac <0-65535>	32
1.2.51	show neighbor lac-ci <0-65535> <0-65535>	32
1.2.52	show nri	32
1.2.53	show online-help	33
1.2.54	show pid	33
1.2.55	show rate-counters [skip-zero]	33

1.2.56	show sgs-connections . . . . .	34
1.2.57	show sms-queue . . . . .	34
1.2.58	show statistics . . . . .	34
1.2.59	show stats [skip-zero] . . . . .	35
1.2.60	show stats level (global peer subscriber) [skip-zero] . . . . .	35
1.2.61	show subscriber (msisdn extension imsi tmsi) ID [(conn trans conn+trans)] . . . . .	36
1.2.62	show subscriber cache [(conn trans conn+trans)] . . . . .	36
1.2.63	show talloc-context (application global all) (full brief DEPTH) . . . . .	37
1.2.64	show talloc-context (application global all) (full brief DEPTH) filter REGEXP . . . . .	38
1.2.65	show talloc-context (application global all) (full brief DEPTH) tree ADDRESS . . . . .	38
1.2.66	show timer [(v l m g w m n c l s c p l g e r a n l u t a n s g s)] [T N N N N] . . . . .	39
1.2.67	show transaction . . . . .	40
1.2.68	show uptime . . . . .	40
1.2.69	show version . . . . .	40
1.2.70	sms delete expired . . . . .	41
1.2.71	sms send pending . . . . .	41
1.2.72	subscriber (msisdn extension imsi tmsi) ID ms-test close-loop (a b c d e f i) . . . . .	41
1.2.73	subscriber (msisdn extension imsi tmsi) ID ms-test open-loop . . . . .	42
1.2.74	subscriber (msisdn extension imsi tmsi) ID paging . . . . .	43
1.2.75	subscriber (msisdn extension imsi tmsi) ID silent-call start (any tch ftch h... . . . .	44
1.2.76	subscriber (msisdn extension imsi tmsi) ID silent-call stop . . . . .	45
1.2.77	subscriber (msisdn extension imsi tmsi) ID silent-sms sender (msisdn extension ... . . . .	46
1.2.78	subscriber (msisdn extension imsi tmsi) ID sms sender (msisdn extension imsi ... . . . .	47
1.2.79	subscriber (msisdn extension imsi tmsi) ID ussd-notify (0 1 2) .TEXT . . . . .	48
1.2.80	terminal length <0-512> . . . . .	48
1.2.81	terminal no length . . . . .	49
1.2.82	who . . . . .	49
1.3	enable . . . . .	49
1.3.1	configure terminal . . . . .	50
1.3.2	copy running-config startup-config . . . . .	50
1.3.3	disable . . . . .	50
1.3.4	logging color (0 1) . . . . .	51
1.3.5	logging disable . . . . .	51
1.3.6	logging enable . . . . .	51
1.3.7	logging filter all (0 1) . . . . .	52
1.3.8	logging filter imsi IMSI . . . . .	52
1.3.9	logging level (r l l c l m m l r l m n c l p a g m s c m g c p h o l d b l e f c t r l s m p l r a n a p l v r i u c s ... . . . .	53
1.3.10	logging level force-all (debug info notice error fatal) . . . . .	56
1.3.11	logging level set-all (debug info notice error fatal) . . . . .	56

1.3.12	logging print category (0 1) . . . . .	57
1.3.13	logging print category-hex (0 1) . . . . .	57
1.3.14	logging print extended-timestamp (0 1) . . . . .	58
1.3.15	logging print file (0 1 basename) [last] . . . . .	58
1.3.16	logging print level (0 1) . . . . .	59
1.3.17	logging print thread-id (0 1) . . . . .	59
1.3.18	logging set-log-mask MASK . . . . .	60
1.3.19	logging timestamp (0 1) . . . . .	60
1.3.20	logp (rllccllmmlrrlrmncc paglmsclmgcplholdblreflctrlsmpp ranapl rlrliucslbssap sg... . . . .	61
1.3.21	mgw <0-255> block . . . . .	64
1.3.22	mgw <0-255> reconnect . . . . .	64
1.3.23	mgw <0-255> unblock . . . . .	65
1.3.24	no logging level force-all . . . . .	65
1.3.25	show alarms . . . . .	65
1.3.26	show asciidoc counters . . . . .	66
1.3.27	show bsc . . . . .	66
1.3.28	show connection [trans] . . . . .	66
1.3.29	show cpu-sched threads . . . . .	67
1.3.30	show cs7 (sualm3ualipa) [<0-65534>] . . . . .	67
1.3.31	show cs7 config . . . . .	68
1.3.32	show cs7 instance <0-15> as (active all m3ualsua) . . . . .	68
1.3.33	show cs7 instance <0-15> asp . . . . .	69
1.3.34	show cs7 instance <0-15> route . . . . .	69
1.3.35	show cs7 instance <0-15> sccp addressbook . . . . .	70
1.3.36	show cs7 instance <0-15> sccp connections . . . . .	70
1.3.37	show cs7 instance <0-15> sccp ssn <0-65535> . . . . .	71
1.3.38	show cs7 instance <0-15> sccp timers . . . . .	71
1.3.39	show cs7 instance <0-15> sccp users . . . . .	72
1.3.40	show cs7 instance <0-15> users . . . . .	72
1.3.41	show fsm NAME . . . . .	73
1.3.42	show fsm all . . . . .	73
1.3.43	show fsm-instances NAME . . . . .	73
1.3.44	show fsm-instances all . . . . .	74
1.3.45	show history . . . . .	74
1.3.46	show logging vty . . . . .	74
1.3.47	show mgw-pool . . . . .	75
1.3.48	show neighbor . . . . .	75
1.3.49	show neighbor (aliu) . . . . .	75
1.3.50	show neighbor (aliu) (ran-pclmsc-ipa-name) RAN_PC_OR_MSC_IPA_NAME . . . . .	76

1.3.51	show neighbor (aliu) cgi <0-999> <0-999> <0-65535> <0-65535> . . . . .	76
1.3.52	show neighbor (aliu) lac <0-65535> . . . . .	77
1.3.53	show neighbor (aliu) lac-ci <0-65535> <0-65535> . . . . .	77
1.3.54	show neighbor cgi <0-999> <0-999> <0-65535> <0-65535> . . . . .	78
1.3.55	show neighbor lac <0-65535> . . . . .	79
1.3.56	show neighbor lac-ci <0-65535> <0-65535> . . . . .	79
1.3.57	show nri . . . . .	79
1.3.58	show online-help . . . . .	80
1.3.59	show rate-counters [skip-zero] . . . . .	80
1.3.60	show sgs-connections . . . . .	80
1.3.61	show sms-queue . . . . .	81
1.3.62	show startup-config . . . . .	81
1.3.63	show statistics . . . . .	81
1.3.64	show stats [skip-zero] . . . . .	82
1.3.65	show stats level (global peer subscriber) [skip-zero] . . . . .	82
1.3.66	show subscriber (msisdn extension imsi tmsi id) ID [(conn trans conn+trans)] . . . . .	83
1.3.67	show subscriber cache [(conn trans conn+trans)] . . . . .	83
1.3.68	show talloc-context (application global all) (full brief DEPTH) . . . . .	84
1.3.69	show talloc-context (application global all) (full brief DEPTH) filter REGEXP . . . . .	85
1.3.70	show talloc-context (application global all) (full brief DEPTH) tree ADDRESS . . . . .	85
1.3.71	show timer [(v l m g w m n c l s c p l e r a n l u t r a n s g s)] [T N N N N] . . . . .	86
1.3.72	show transaction . . . . .	87
1.3.73	show version . . . . .	87
1.3.74	shutdown . . . . .	87
1.3.75	sms delete expired . . . . .	88
1.3.76	sms send pending . . . . .	88
1.3.77	sms-queue clear . . . . .	88
1.3.78	sms-queue max-failure <1-500> . . . . .	89
1.3.79	sms-queue max-pending <1-500> . . . . .	89
1.3.80	sms-queue trigger . . . . .	89
1.3.81	stats report . . . . .	90
1.3.82	stats reset . . . . .	90
1.3.83	subscriber (msisdn extension imsi tmsi id) ID expire . . . . .	90
1.3.84	subscriber (msisdn extension imsi tmsi id) ID ms-test close-loop (a b c d e f i) . . . . .	91
1.3.85	subscriber (msisdn extension imsi tmsi id) ID ms-test open-loop . . . . .	92
1.3.86	subscriber (msisdn extension imsi tmsi id) ID paging . . . . .	93
1.3.87	subscriber (msisdn extension imsi tmsi id) ID silent-call start (a n y l t c h / f l t c h / h ... . . . .	93
1.3.88	subscriber (msisdn extension imsi tmsi id) ID silent-call stop . . . . .	95
1.3.89	subscriber (msisdn extension imsi tmsi id) ID silent-sms sender (msisdn extension ... . . . .	95

1.3.90	subscriber (msisdnextensionlimsiltmsilid) ID sms delete-all	96
1.3.91	subscriber (msisdnextensionlimsiltmsilid) ID sms pending-send	97
1.3.92	subscriber (msisdnextensionlimsiltmsilid) ID sms sender (msisdnextensionlimsil...	98
1.3.93	subscriber (msisdnextensionlimsiltmsilid) ID ussd-notify (0/1/2) .TEXT	99
1.3.94	terminal length <0-512>	99
1.3.95	terminal monitor	100
1.3.96	terminal no length	100
1.3.97	terminal no monitor	101
1.3.98	who	101
1.4	config	101
1.4.1	banner motd default	101
1.4.2	banner motd file [FILE]	102
1.4.3	cpu-sched	102
1.4.4	cs7 instance <0-15>	102
1.4.5	ctrl	103
1.4.6	enable password (8l) WORD	103
1.4.7	enable password LINE	103
1.4.8	hlr	104
1.4.9	hostname WORD	104
1.4.10	line vty	104
1.4.11	log alarms <2-32700>	105
1.4.12	log file FILENAME [blocking-io]	105
1.4.13	log gsmmap [HOSTNAME]	105
1.4.14	log stderr [blocking-io]	106
1.4.15	log syslog (authpriv cron daemon ftp lpr mail news user uucp)	106
1.4.16	log syslog local <0-7>	107
1.4.17	log systemd-journal [raw]	107
1.4.18	mncc-int	107
1.4.19	msc	108
1.4.20	network	108
1.4.21	no banner motd	108
1.4.22	no enable password	109
1.4.23	no hostname [HOSTNAME]	109
1.4.24	no log alarms	109
1.4.25	no log file FILENAME	110
1.4.26	no log gsmmap [HOSTNAME]	110
1.4.27	no log stderr	110
1.4.28	no log syslog	111
1.4.29	no log systemd-journal	111

1.4.30	no service advanced-vty . . . . .	111
1.4.31	no service terminal-length [<0-512>] . . . . .	112
1.4.32	no stats reporter log [NAME] . . . . .	112
1.4.33	no stats reporter statsd [NAME] . . . . .	113
1.4.34	password (8l) WORD . . . . .	113
1.4.35	password LINE . . . . .	113
1.4.36	service advanced-vty . . . . .	114
1.4.37	service terminal-length <0-512> . . . . .	114
1.4.38	sgs . . . . .	114
1.4.39	show history . . . . .	115
1.4.40	smc . . . . .	115
1.4.41	stats interval <0-65535> . . . . .	115
1.4.42	stats reporter log [NAME] . . . . .	116
1.4.43	stats reporter statsd [NAME] . . . . .	116
1.4.44	stats-tcp batch-size <1-65535> . . . . .	116
1.4.45	stats-tcp interval <0-65535> . . . . .	117
1.5	config-log . . . . .	117
1.5.1	logging color (0l1) . . . . .	117
1.5.2	logging filter all (0l1) . . . . .	118
1.5.3	logging filter imsi IMSI . . . . .	118
1.5.4	logging level (rllclmmllrrlmmncclpaglmsclmgcplholdblreflctrlsmpplranaplvrluics... . . . .	119
1.5.5	logging level force-all (debuglinfofnoticeerrorlfatal) . . . . .	122
1.5.6	logging level set-all (debuglinfofnoticeerrorlfatal) . . . . .	122
1.5.7	logging print category (0l1) . . . . .	123
1.5.8	logging print category-hex (0l1) . . . . .	123
1.5.9	logging print extended-timestamp (0l1) . . . . .	124
1.5.10	logging print file (0l1 basename) [last] . . . . .	124
1.5.11	logging print level (0l1) . . . . .	125
1.5.12	logging print thread-id (0l1) . . . . .	125
1.5.13	logging timestamp (0l1) . . . . .	126
1.5.14	no logging level force-all . . . . .	126
1.6	config-stats . . . . .	127
1.6.1	disable . . . . .	127
1.6.2	enable . . . . .	127
1.6.3	flush-period <0-65535> . . . . .	127
1.6.4	level (globalpeerlsubscriber) . . . . .	128
1.6.5	local-ip ADDR . . . . .	128
1.6.6	mtu <100-65535> . . . . .	128
1.6.7	no local-ip . . . . .	129

1.6.8	no mtu	129
1.6.9	no prefix	129
1.6.10	prefix PREFIX	130
1.6.11	remote-ip ADDR	130
1.6.12	remote-port <1-65535>	130
1.7	config-line	131
1.7.1	bind A.B.C.D [<0-65535>]	131
1.7.2	login	131
1.7.3	no login	131
1.8	config-ctrl	132
1.8.1	bind A.B.C.D	132
1.9	config-cs7	132
1.9.1	as NAME (sualm3ualipa)	132
1.9.2	asp NAME <0-65535> <0-65535> (sualm3ualipa)	133
1.9.3	description .TEXT	133
1.9.4	network-indicator (international   national   reserved   spare)	134
1.9.5	no as NAME	134
1.9.6	no asp NAME	135
1.9.7	no sccp-address NAME	135
1.9.8	point-code POINT_CODE	136
1.9.9	point-code delimiter (defaultldash)	136
1.9.10	point-code format <1-24> [<1-23>] [<1-22>]	137
1.9.11	point-code format default	137
1.9.12	sccp-address NAME	138
1.9.13	sccp-timer (conn_esttlasliarllrepeat_rellintlguardlresetlreassembly) <1-99999...	138
1.9.14	xua rkm routing-key-allocation (static-only dynamic-permitted)	139
1.10	config-cs7-as	140
1.10.1	asp NAME	140
1.10.2	description .TEXT	140
1.10.3	no asp NAME	140
1.10.4	no traffic-mode	141
1.10.5	point-code override dpc PC	141
1.10.6	point-code override patch-sccp (disabledlboth)	142
1.10.7	qos-class <0-255>	142
1.10.8	recovery-timeout <1-2000>	143
1.10.9	routing-key RCONTEXT DPC	143
1.10.10	routing-key RCONTEXT DPC si (aal2lbicclb-isuplh248lisuplsat-isuplsccpltup)	144
1.10.11	routing-key RCONTEXT DPC si (aal2lbicclb-isuplh248lisuplsat-isuplsccpltup) ssn S...	145
1.10.12	routing-key RCONTEXT DPC ssn SSN	146

1.10.13 traffic-mode (broadcast   loadshare   roundrobin   override)	146
1.11 config-cs7-asp	147
1.11.1 block	147
1.11.2 description TEXT	147
1.11.3 local-ip (A.B.C.D X:X::X:X)	147
1.11.4 no quirk (no_notify daud_in_asplnm_inactive)	148
1.11.5 qos-class <0-255>	148
1.11.6 quirk (no_notify daud_in_asplnm_inactive)	149
1.11.7 remote-ip (A.B.C.D X:X::X:X)	149
1.11.8 role (sglasplisp)	150
1.11.9 sctp-role (client server)	150
1.11.10 shutdown	151
1.12 config-cs7-sccpaddr	151
1.12.1 global-title	151
1.12.2 no global-title	151
1.12.3 no point-code	152
1.12.4 no subsystem-number	152
1.12.5 point-code POINT_CODE	152
1.12.6 routing-indicator (GT PC IP)	153
1.12.7 subsystem-number <0-4294967295>	153
1.13 config-cs7-sccpaddr-gt	154
1.13.1 digits DIGITS	154
1.13.2 global-title-indicator <0-15>	154
1.13.3 nature-of-address-indicator <0-127>	155
1.13.4 numbering-plan-indicator <0-15>	155
1.13.5 translation-type <0-255>	155
1.14 config-cpu-sched	156
1.14.1 cpu-affinity (self all <0-4294967295> THREADNAME) CPUHEXMASK [delay]	156
1.14.2 policy rr <1-32>	157
1.15 config-net	157
1.15.1 authentication (optional required)	157
1.15.2 call-waiting	157
1.15.3 encryption a5 <0-4> [<0-4>] [<0-4>] [<0-4>] [<0-4>]	158
1.15.4 encryption uea <0-2> [<0-2>] [<0-2>]	158
1.15.5 long name NAME	159
1.15.6 mgw <0-255>	159
1.15.7 mm info (0 1)	159
1.15.8 mobile network code <0-999>	160
1.15.9 network country code <1-999>	160

1.15.10 no call-waiting . . . . .	160
1.15.11 no mgw <0-255> . . . . .	161
1.15.12 no timezone . . . . .	161
1.15.13 rrlp mode (nonelms-basedlms-preferredlass-preferred) . . . . .	161
1.15.14 short name NAME . . . . .	162
1.15.15 timezone <-19-19> (0 15 30 45) . . . . .	162
1.15.16 timezone <-19-19> (0 15 30 45) <0-2> . . . . .	163
1.16 config-mgw . . . . .	163
1.16.1 description .TEXT . . . . .	163
1.16.2 endpoint-domain NAME . . . . .	164
1.16.3 local-ip (A.B.C.D X::X::X:X) . . . . .	164
1.16.4 local-port <0-65535> . . . . .	164
1.16.5 no reset-endpoint NAME . . . . .	165
1.16.6 remote-ip (A.B.C.D X::X::X:X) . . . . .	165
1.16.7 remote-port <0-65535> . . . . .	165
1.16.8 reset-endpoint NAME . . . . .	166
1.17 config-msc . . . . .	166
1.17.1 asn1 debug (1 0) . . . . .	166
1.17.2 asn1 xer-print (1 0) . . . . .	166
1.17.3 assign-tmsi . . . . .	167
1.17.4 auth-tuple-max-reuse-count <-1-2147483647> . . . . .	167
1.17.5 auth-tuple-reuse-on-error (0 1) . . . . .	167
1.17.6 check-imei-rqd (0 1 early) . . . . .	168
1.17.7 cs7-instance-a <0-15> . . . . .	168
1.17.8 cs7-instance-iu <0-15> . . . . .	168
1.17.9 emergency-call route-to-msisdn MSISDN . . . . .	169
1.17.10 handover-number range MSISDN_FIRST MSISDN_LAST . . . . .	169
1.17.11 iu rab-assign-addr-enc (x213 v4raw) . . . . .	169
1.17.12 lcls-permitted . . . . .	170
1.17.13 mncc external MNCC_SOCKET_PATH . . . . .	170
1.17.14 mncc guard-timeout <0-255> . . . . .	170
1.17.15 mncc internal . . . . .	171
1.17.16 ncsc guard-timeout <0-255> . . . . .	171
1.17.17 neighbor (aliu) cgi <0-999> <0-999> <0-65535> <0-65535> (ran-pclmsc-ipa-name) RA... . . . .	171
1.17.18 neighbor (aliu) lac <0-65535> (ran-pclmsc-ipa-name) RAN_PC_OR_MSC_IPA_NAME . . . . .	172
1.17.19 neighbor (aliu) lac-ci <0-65535> <0-65535> (ran-pclmsc-ipa-name) RAN_PC_OR_MSC_I... . . . .	173
1.17.20 no assign-tmsi . . . . .	173
1.17.21 no lcls-permitted . . . . .	174
1.17.22 no neighbor (aliu) (ran-pclmsc-ipa-name) RAN_PC_OR_MSC_IPA_NAME . . . . .	174

1.17.23 no sms-over-gsup . . . . .	175
1.17.24 nri add <0-32767> [<0-32767>] . . . . .	175
1.17.25 nri bitlen <0-15> . . . . .	175
1.17.26 nri del <0-32767> [<0-32767>] . . . . .	176
1.17.27 osmux (onloffonly) . . . . .	176
1.17.28 sms-over-gsup . . . . .	176
1.17.29 timer [(vrlmgwlmncclscclpgeranlutanlsgs)] [TNNNN] [(<0-2147483647> default)] . . . . .	177
1.18 config-mncc-int . . . . .	177
1.18.1 default-codec tch-f (frlefrlamr) . . . . .	178
1.18.2 default-codec tch-h (hrlamr) . . . . .	178
1.19 config-hlr . . . . .	179
1.19.1 ipa-name NAME . . . . .	179
1.19.2 remote-ip A.B.C.D . . . . .	179
1.19.3 remote-port <1-65535> . . . . .	179
1.20 config-sgs . . . . .	180
1.20.1 counter (ns7lms11) <0-255> . . . . .	180
1.20.2 local-ip A.B.C.D . . . . .	180
1.20.3 local-port <0-65535> . . . . .	180
1.20.4 timer (ts5lts6-2lts7lts11lts14lts15) <1-120> . . . . .	181
1.20.5 vlr-name FQDN . . . . .	181
1.21 config-smsc . . . . .	182
1.21.1 database PATH . . . . .	182
1.21.2 database delete-delivered (0 1) . . . . .	182
1.21.3 database delete-expired (0 1) . . . . .	182
1.21.4 queue max-failure <1-500> . . . . .	183
1.21.5 queue max-pending <1-500> . . . . .	183
1.21.6 validity-period (minimum default) <1-5256000> . . . . .	183

# List of Tables

1.1	VTY Parameter Patterns . . . . .	1
1.2	VTY port numbers . . . . .	1

# Chapter 1

## VTY reference

The Virtual Tele Type (VTY) has the concept of nodes and commands. This chapter lists all nodes and the commands that are available within the node. Each command can consist out of several words followed by a variable number of parameters. There are common patterns for the parameters, these include IPv4 addresses, number ranges, a word, a line of text and choice. The following will explain the commonly used patterns.

Pattern	Example	Explanation
A.B.C.D	127.0.0.1	A IPv4 address
TEXT	example01	A single string without any spaces, tabs
.TEXT	Some information	A line of text
(OptionA OptionB OptionC)	OptionA	A choice between a list of available options
<0-10>	5	A number from a range

Table 1.1: VTY Parameter Patterns

The application is configured through the VTY. For configuring a system one needs to enter the **enable** node and then enter the **configure terminal** command. Then the configuration can be made according to the available commands. After the system has been configured one can use the **write** command to write the new configuration to the configuration file. The new file will be used after the application has been restarted.

The following table lists the TCP port numbers of the VTY for the various Osmocom GSM related programs as used on sysmocom products:

Port Number	Software
4240	osmo-pcu
4241	osmo-bts
4242	osmo-nitb, osmo-bsc
4243	osmo-bsc_mgcp
4244	osmo-bsc_nat
4245	osmo-sgsn
4246	osmo-gbproxy

Table 1.2: VTY port numbers

### 1.1 Common Commands

These commands are available on all VTY nodes. They are listed here only once, to unclutter the VTY reference.

### 1.1.1 end

#### Command

```
end
```

#### Parameters

end

End current mode and change to enable mode.

### 1.1.2 exit

#### Command

```
exit
```

#### Parameters

exit

Exit current mode and down to previous mode

### 1.1.3 help

#### Command

```
help
```

#### Parameters

help

Description of the interactive help system

### 1.1.4 list [with-flags]

#### Command

```
list [with-flags]
```

#### Parameters

list

Print command list

[with-flags]

Also print the VTY attribute flags

---

### 1.1.5 show running-config

#### Command

```
show running-config
```

#### Parameters

##### show

Show running system information

##### running-config

running configuration

### 1.1.6 show vty-attributes

#### Command

```
show vty-attributes
```

#### Parameters

##### show

Show running system information

##### vty-attributes

List of VTY attributes

### 1.1.7 show vty-attributes (application|library|global)

#### Command

```
show vty-attributes (application|library|global)
```

#### Parameters

##### show

Show running system information

##### vty-attributes

List of VTY attributes

##### application

Application specific attributes only

##### library

Library specific attributes only

##### global

Global attributes only

---

### 1.1.8 write

#### Command

```
write
```

#### Parameters

##### write

Write running configuration to memory, network, or terminal

### 1.1.9 write file [PATH]

#### Command

```
write file [PATH]
```

#### Parameters

##### write

Write running configuration to memory, network, or terminal

##### file

Write to configuration file

##### [PATH]

Set file path to store the config, or replace if already exists

### 1.1.10 write memory

#### Command

```
write memory
```

#### Parameters

##### write

Write running configuration to memory, network, or terminal

##### memory

Write configuration to the file (same as write file)

### 1.1.11 write terminal

#### Command

```
write terminal
```

#### Parameters

##### write

Write running configuration to memory, network, or terminal

##### terminal

Write to terminal

## 1.2 view

The view node is the default node when connecting to the VTY interface. This node does not require any additional permission and allows to introspect the application.

### 1.2.1 enable [expert-mode]

#### Command

```
enable [expert-mode]
```

#### Parameters

##### enable

Turn on privileged mode command

##### [expert-mode]

Enable the expert mode (show hidden commands)

### 1.2.2 logging color (0|1)

#### Command

```
logging color (0|1)
```

#### Parameters

##### logging

Configure logging

##### color

Configure color-printing for log messages

##### 0

Don't use color for printing messages

##### 1

Use color for printing messages

---

### 1.2.3 logging disable

#### Command

```
logging disable
```

#### Parameters

##### logging

Configure logging

##### disable

Disables logging to this vty

### 1.2.4 logging enable

This command is required to make logging commands available on the telnet VTY.

#### Command

```
logging enable
```

#### Parameters

##### logging

Configure logging

##### enable

Enables logging to this vty

### 1.2.5 logging filter all (0|1)

Disable/enable general log output on a given target. Typically, 'logging filter all 1' allows to see the usual log output on a given target. Setting to '0' can be useful when logging to the telnet VTY console: mute all log output to allow typing VTY commands on the telnet prompt without interference from log output; 'logging filter all 1' then re-enables logging in the same log output configuration as before. Some applications provide more specific filters, e.g. to log a given IMSI only. To employ such filters, set 'logging filter all 0' to disable general logging, and then enable a more specific filter instead.

#### Command

```
logging filter all (0|1)
```

#### Parameters

##### logging

Configure logging

##### filter

Filter log messages

---

all

Do you want to log all messages?

0

Only print messages matched by other filters

1

Bypass filter and print all messages

## 1.2.6 logging filter imsi IMSI

Command

```
logging filter imsi IMSI
```

Parameters

logging

Configure logging

filter

Filter log messages

imsi

Filter log messages by IMSI

IMSI

IMSI to be used as filter

## 1.2.7 logging level (rll|cc|mm|rr|mncc|pag|msc|mgcp|ho|db|ref|ctrl|smpp|ranap|vlr|iucs...

Command

```
logging level (rll|cc|mm|rr|mncc|pag|msc|mgcp|ho|db|ref|ctrl|smpp|ranap|vlr|iucs|bssap| ↵
sgs|ss|lglobal|llapd|linp|lmux|lmi|lmib|lsms|lctrl|lgtp|lstats|lgsup|loap|lss7| ↵
lscpp|lsua|lm3ua|lmgcp|ljibuf|lrspro|lns|lbssgp|lndata|lnssignal|liuup|lpfcp|lcsn1 ↵
) (debug|info|notice|error|fatal)
```

Parameters

logging

Configure logging

level

Set the log level for a specified category

rll

A-bis Radio Link Layer (RLL)

cc

Layer3 Call Control (CC)

---

mm	Layer3 Mobility Management (MM)
rr	Layer3 Radio Resource (RR)
mncc	MNCC API for Call Control application
pag	Paging Subsystem
msc	Mobile Switching Center
mgcp	Media Gateway Control Protocol
ho	Hand-Over
db	Database Layer
ref	Reference Counting
ctrl	Control interface
smpp	SMPP interface for external SMS apps
ranap	Radio Access Network Application Part Protocol
vlr	Visitor Location Register
iucs	Iu-CS Protocol
bssap	BSSAP Protocol (A Interface)
sgs	SGs Interface (SGsAP)
ss	Supplementary Services
lglobal	Library-internal global log family
llapd	LAPD in libosmogsm

---

---

linp  
A-bis Input Subsystem

lmux  
A-bis B-Subchannel TRAU Frame Multiplex

lmi  
A-bis Input Driver for Signalling

lmib  
A-bis Input Driver for B-Channels (voice)

lsms  
Layer3 Short Message Service (SMS)

lctrl  
Control Interface

lgtp  
GPRS GTP library

lstats  
Statistics messages and logging

lgsup  
Generic Subscriber Update Protocol

loap  
Osmocom Authentication Protocol

lss7  
libosmo-sigtran Signalling System 7

lsccp  
libosmo-sigtran SCCP Implementation

lsua  
libosmo-sigtran SCCP User Adaptation

lm3ua  
libosmo-sigtran MTP3 User Adaptation

lmgcp  
libosmo-mgcp Media Gateway Control Protocol

ljibuf  
libosmo-netif Jitter Buffer

lrspro  
Remote SIM protocol

lns  
GPRS NS layer

lbssgp  
GPRS BSSGP layer

---

Insdata

GPRS NS layer data PDU

Inssignal

GPRS NS layer signal PDU

Iuup

Iu UP layer

lpfcp

libosmo-pfcp Packet Forwarding Control Protocol

lcsn1

libosmo-csn1 Concrete Syntax Notation 1 codec

debug

Log debug messages and higher levels

info

Log informational messages and higher levels

notice

Log noticeable messages and higher levels

error

Log error messages and higher levels

fatal

Log only fatal messages

### 1.2.8 logging level force-all (debug|info|notice|error|fatal)

Command

```
logging level force-all (debug|info|notice|error|fatal)
```

Parameters

logging

Configure logging

level

Set the log level for a specified category

force-all

Globally force all logging categories to a specific level. This is released by the 'no logging level force-all' command. Note: any 'logging level <category> <level>' commands will have no visible effect after this, until the forced level is released.

debug

Log debug messages and higher levels

info

Log informational messages and higher levels

notice

Log noticeable messages and higher levels

error

Log error messages and higher levels

fatal

Log only fatal messages

### 1.2.9 logging level set-all (debug|info|notice|error|fatal)

Command

```
logging level set-all (debug|info|notice|error|fatal)
```

Parameters

logging

Configure logging

level

Set the log level for a specified category

set-all

Once-off set all categories to the given log level. There is no single command to take back these changes -- each category is set to the given level, period.

debug

Log debug messages and higher levels

info

Log informational messages and higher levels

notice

Log noticeable messages and higher levels

error

Log error messages and higher levels

fatal

Log only fatal messages

### 1.2.10 logging print category (0|1)

Command

```
logging print category (0|1)
```

Parameters

---

logging

Configure logging

print

Log output settings

category

Configure log message

0

Don't prefix each log message

1

Prefix each log message with category/subsystem name

### 1.2.11 logging print category-hex (0|1)

Command

```
logging print category-hex (0|1)
```

Parameters

logging

Configure logging

print

Log output settings

category-hex

Configure log message

0

Don't prefix each log message

1

Prefix each log message with category/subsystem nr in hex ('<000b>')

### 1.2.12 logging print extended-timestamp (0|1)

Command

```
logging print extended-timestamp (0|1)
```

Parameters

logging

Configure logging

print

Log output settings

extended-timestamp

Configure log message timestamping

0

Don't prefix each log message

1

Prefix each log message with current timestamp with YYYYMMDDhhmmssnnn

### 1.2.13 logging print file (0|1|basename) [last]

Command

```
logging print file (0|1|basename) [last]
```

Parameters

logging

Configure logging

print

Log output settings

file

Configure log message

0

Don't prefix each log message

1

Prefix each log message with the source file and line

basename

Prefix each log message with the source file's basename (strip leading paths) and line

[last]

Log source file info at the end of a log line. If omitted, log source file info just before the log text.

### 1.2.14 logging print level (0|1)

Command

```
logging print level (0|1)
```

Parameters

---

logging

Configure logging

print

Log output settings

level

Configure log message

0

Don't prefix each log message

1

Prefix each log message with the log level name

### 1.2.15 logging print thread-id (0|1)

Command

```
logging print thread-id (0|1)
```

Parameters

logging

Configure logging

print

Log output settings

thread-id

Configure log message logging Thread ID

0

Don't prefix each log message

1

Prefix each log message with current Thread ID

### 1.2.16 logging set-log-mask MASK

Command

```
logging set-log-mask MASK
```

Parameters

logging

Configure logging

set-log-mask

Set the logmask of this logging target

MASK

List of logging categories to log, e.g. 'abc:mno:xyz'. Available log categories depend on the specific application, refer to the 'logging level' command. Optionally add individual log levels like 'abc,1:mno,3:xyz,5', where the level numbers are LOGL\_DEBUG=1 LOGL\_INFO=3 LOGL\_NOTICE=5 LOGL\_ERROR=7 LOGL\_FATAL=8

### 1.2.17 logging timestamp (0|1)

#### Command

```
logging timestamp (0|1)
```

#### Parameters

##### logging

Configure logging

##### timestamp

Configure log message timestamping

0

Don't prefix each log message

1

Prefix each log message with current timestamp

### 1.2.18 logp (rll|cc|mm|rr|mncc|pag|msc|mgcp|ho|db|ref|ctrl|smpp|ranap|vlr|iucs|bssap|sg...

#### Command

```
logp (rll|cc|mm|rr|mncc|pag|msc|mgcp|ho|db|ref|ctrl|smpp|ranap|vlr|iucs|bssap|sgs|ss| ↵
lglobal|llapd|linp|lmux|lmi|lmib|lsms|lctrl|lgtp|lstats|lgsup|loap|lss7|lsccp|lsua| ↵
lm3ua|lmgcp|ljibuf|lrspro|lns|lbssgp|lnsdata|lnssignal|liuup|lpfcp|lcsn1) (debug| ↵
info|notice|error|fatal) .LOGMESSAGE
```

#### Parameters

##### logp

Print a message on all log outputs; useful for placing markers in test logs

##### rll

A-bis Radio Link Layer (RLL)

##### cc

Layer3 Call Control (CC)

##### mm

Layer3 Mobility Management (MM)

##### rr

Layer3 Radio Resource (RR)

##### mncc

MNCC API for Call Control application

##### pag

Paging Subsystem

---

msc	Mobile Switching Center
mgcp	Media Gateway Control Protocol
ho	Hand-Over
db	Database Layer
ref	Reference Counting
ctrl	Control interface
smpp	SMPP interface for external SMS apps
ranap	Radio Access Network Application Part Protocol
vlr	Visitor Location Register
iucs	Iu-CS Protocol
bssap	BSSAP Protocol (A Interface)
sgs	SGs Interface (SGsAP)
ss	Supplementary Services
lglobal	Library-internal global log family
llapd	LAPD in libosmogsm
linp	A-bis Input Subsystem
lmux	A-bis B-Subchannel TRAU Frame Multiplex
lmi	A-bis Input Driver for Signalling
lmib	A-bis Input Driver for B-Channels (voice)

---

---

lsms  
Layer3 Short Message Service (SMS)

lctrl  
Control Interface

lgtp  
GPRS GTP library

lstats  
Statistics messages and logging

lgsup  
Generic Subscriber Update Protocol

loap  
Osmocom Authentication Protocol

lss7  
libosmo-sigtran Signalling System 7

lsccp  
libosmo-sigtran SCCP Implementation

lsua  
libosmo-sigtran SCCP User Adaptation

lm3ua  
libosmo-sigtran MTP3 User Adaptation

lmgcp  
libosmo-mgcp Media Gateway Control Protocol

ljibuf  
libosmo-netif Jitter Buffer

lrspro  
Remote SIM protocol

lns  
GPRS NS layer

lbssgp  
GPRS BSSGP layer

lnsdata  
GPRS NS layer data PDU

lnssignal  
GPRS NS layer signal PDU

liuup  
Iu UP layer

lpfcp  
libosmo-pfcp Packet Forwarding Control Protocol

---

lcsn1

libosmo-csn1 Concrete Syntax Notation 1 codec

debug

Log debug messages and higher levels

info

Log informational messages and higher levels

notice

Log noticeable messages and higher levels

error

Log error messages and higher levels

fatal

Log only fatal messages

.LOGMESSAGE

Arbitrary message to log on given category and log level

### 1.2.19 no logging level force-all

Command

```
no logging level force-all
```

Parameters

no

Negate a command or set its defaults

logging

Configure logging

level

Set the log level for a specified category

force-all

Release any globally forced log level set with 'logging level force-all <level>'

### 1.2.20 show alarms

Command

```
show alarms
```

Parameters

show

Show running system information

alarms

Show current logging configuration

### 1.2.21 show asciidoc counters

#### Command

```
show asciidoc counters
```

#### Parameters

##### show

Show running system information

##### asciidoc

Asciidoc generation

##### counters

Generate table of all registered counters

### 1.2.22 show bsc

#### Command

```
show bsc
```

#### Parameters

##### show

Show running system information

##### bsc

BSC

### 1.2.23 show connection [trans]

#### Command

```
show connection [trans]
```

#### Parameters

##### show

Show running system information

##### connection

Subscriber Connections

##### [trans]

Show child transactions of each connection

---

### 1.2.24 show cpu-sched threads

#### Command

```
show cpu-sched threads
```

#### Parameters

##### show

Show running system information

##### cpu-sched

Show Sched section information

##### threads

Show information about running threads)

### 1.2.25 show cs7 (sua|m3ua|ipa) [<0-65534>]

#### Command

```
show cs7 (sua|m3ua|ipa) [<0-65534>]
```

#### Parameters

##### show

Show running system information

##### cs7

ITU-T Signaling System 7

##### sua

SCCP User Adaptation

##### m3ua

MTP3 User Adaptation

##### ipa

IPA Multiplex (SCCP Lite)

##### [<0-65534>]

Port Number

---

### 1.2.26 show cs7 config

#### Command

```
show cs7 config
```

#### Parameters

##### show

Show running system information

##### cs7

ITU-T Signaling System 7

##### config

Currently running cs7 configuration

### 1.2.27 show cs7 instance <0-15> as (active|all|m3ua|sua)

#### Command

```
show cs7 instance <0-15> as (active|all|m3ua|sua)
```

#### Parameters

##### show

Show running system information

##### cs7

ITU-T Signaling System 7

##### instance

An instance of the SS7 stack

##### <0-15>

An instance of the SS7 stack

##### as

Application Server (AS)

##### active

Display all active ASs

##### all

Display all ASs (default)

##### m3ua

Display all m3ua ASs

##### sua

Display all SUA ASs

---

### 1.2.28 show cs7 instance <0-15> asp

#### Command

```
show cs7 instance <0-15> asp
```

#### Parameters

##### show

Show running system information

##### cs7

ITU-T Signaling System 7

##### instance

An instance of the SS7 stack

##### <0-15>

An instance of the SS7 stack

##### asp

Application Server Process (ASP)

### 1.2.29 show cs7 instance <0-15> route

#### Command

```
show cs7 instance <0-15> route
```

#### Parameters

##### show

Show running system information

##### cs7

ITU-T Signaling System 7

##### instance

An instance of the SS7 stack

##### <0-15>

An instance of the SS7 stack

##### route

Routing Table

---

### 1.2.30 show cs7 instance <0-15> sccp addressbook

#### Command

```
show cs7 instance <0-15> sccp addressbook
```

#### Parameters

show

Show running system information

cs7

ITU-T Signaling System 7

instance

An instance of the SS7 stack

<0-15>

An instance of the SS7 stack

sccp

Signalling Connection Control Part

addressbook

List all SCCP addressbook entries

### 1.2.31 show cs7 instance <0-15> sccp connections

#### Command

```
show cs7 instance <0-15> sccp connections
```

#### Parameters

show

Show running system information

cs7

ITU-T Signaling System 7

instance

An instance of the SS7 stack

<0-15>

An instance of the SS7 stack

sccp

Signalling Connection Control Part

connections

Show List of active SCCP connections

---

### 1.2.32 show cs7 instance <0-15> sccp ssn <0-65535>

#### Command

```
show cs7 instance <0-15> sccp ssn <0-65535>
```

#### Parameters

show

Show running system information

cs7

ITU-T Signaling System 7

instance

An instance of the SS7 stack

<0-15>

An instance of the SS7 stack

sccp

Signalling Connection Control Part

ssn

Find an SCCP User registered for the given SSN

<0-65535>

Subsystem Number (SSN)

### 1.2.33 show cs7 instance <0-15> sccp timers

#### Command

```
show cs7 instance <0-15> sccp timers
```

#### Parameters

show

Show running system information

cs7

ITU-T Signaling System 7

instance

An instance of the SS7 stack

<0-15>

An instance of the SS7 stack

sccp

Signaling Connection Control Part

timers

Show List of SCCP timers

### 1.2.34 show cs7 instance <0-15> sccp users

#### Command

```
show cs7 instance <0-15> sccp users
```

#### Parameters

##### show

Show running system information

##### cs7

ITU-T Signaling System 7

##### instance

An instance of the SS7 stack

##### <0-15>

An instance of the SS7 stack

##### sccp

Signalling Connection Control Part

##### users

Show List of SCCP Users registered

### 1.2.35 show cs7 instance <0-15> users

#### Command

```
show cs7 instance <0-15> users
```

#### Parameters

##### show

Show running system information

##### cs7

ITU-T Signaling System 7

##### instance

An instance of the SS7 stack

##### <0-15>

An instance of the SS7 stack

##### users

User Table

---

### 1.2.36 show fsm NAME

#### Command

```
show fsm NAME
```

#### Parameters

##### show

Show running system information

##### fsm

Show information about finite state machines

##### NAME

Display information about a single named finite state machine

### 1.2.37 show fsm all

#### Command

```
show fsm all
```

#### Parameters

##### show

Show running system information

##### fsm

Show information about finite state machines

##### all

Display a list of all registered finite state machines

### 1.2.38 show fsm-instances NAME

#### Command

```
show fsm-instances NAME
```

#### Parameters

##### show

Show running system information

##### fsm-instances

Show information about finite state machine instances

##### NAME

Display a list of all FSM instances of the named finite state machine

---

### 1.2.39 show fsm-instances all

#### Command

```
show fsm-instances all
```

#### Parameters

##### show

Show running system information

##### fsm-instances

Show information about finite state machine instances

##### all

Display a list of all FSM instances of all finite state machine

### 1.2.40 show history

#### Command

```
show history
```

#### Parameters

##### show

Show running system information

##### history

Display the session command history

### 1.2.41 show logging vty

#### Command

```
show logging vty
```

#### Parameters

##### show

Show running system information

##### logging

Show current logging configuration

##### vty

Show current logging configuration for this vty

---

### 1.2.42 show mgw-pool

#### Command

```
show mgw-pool
```

#### Parameters

##### show

Show running system information

##### mgw-pool

Display information about the MGW-Pool

### 1.2.43 show neighbor

#### Command

```
show neighbor
```

#### Parameters

##### show

Show running system information

##### neighbor

Show Handover targets

### 1.2.44 show neighbor (a|iu)

#### Command

```
show neighbor (a|iu)
```

#### Parameters

##### show

Show running system information

##### neighbor

Show Handover targets

##### a

Neighbor on GERAN-A

##### iu

Neighbor on UTRAN-Iu

### 1.2.45 show neighbor (a|iu) (ran-pc|msc-ipa-name) RAN\_PC\_OR\_MSC\_IPA\_NAME

#### Command

```
show neighbor (a|iu) (ran-pc|msc-ipa-name) RAN_PC_OR_MSC_IPA_NAME
```

#### Parameters

##### show

Show running system information

##### neighbor

Show Handover targets

##### a

Neighbor on GERAN-A

##### iu

Neighbor on UTRAN-Iu

##### ran-pc

SCCP point code of RAN peer

##### msc-ipa-name

GSUP IPA name of target MSC

##### RAN\_PC\_OR\_MSC\_IPA\_NAME

Point code or MSC IPA name value

### 1.2.46 show neighbor (a|iu) cgi <0-999> <0-999> <0-65535> <0-65535>

#### Command

```
show neighbor (a|iu) cgi <0-999> <0-999> <0-65535> <0-65535>
```

#### Parameters

##### show

Show running system information

##### neighbor

Show Handover targets

##### a

Neighbor on GERAN-A

##### iu

Neighbor on UTRAN-Iu

##### cgi

Handover target cell by Cell-Global Identifier (MCC, MNC, LAC, CI)

---

<0-999>

MCC

<0-999>

MNC

<0-65535>

LAC

<0-65535>

CI

### 1.2.47 show neighbor (a|iu) lac <0-65535>

Command

```
show neighbor (a|iu) lac <0-65535>
```

Parameters

show

Show running system information

neighbor

Show Handover targets

a

Neighbor on GERAN-A

iu

Neighbor on UTRAN-Iu

lac

Handover target cell by LAC

<0-65535>

LAC

### 1.2.48 show neighbor (a|iu) lac-ci <0-65535> <0-65535>

Command

```
show neighbor (a|iu) lac-ci <0-65535> <0-65535>
```

Parameters

show

Show running system information

neighbor

Show Handover targets

a

Neighbor on GERAN-A

iu

Neighbor on UTRAN-Iu

lac-ci

Handover target cell by LAC and CI

<0-65535>

LAC

<0-65535>

CI

### 1.2.49 show neighbor cgi <0-999> <0-999> <0-65535> <0-65535>

Command

```
show neighbor cgi <0-999> <0-999> <0-65535> <0-65535>
```

Parameters

show

Show running system information

neighbor

Show Handover targets

cgi

Handover target cell by Cell-Global Identifier (MCC, MNC, LAC, CI)

<0-999>

MCC

<0-999>

MNC

<0-65535>

LAC

<0-65535>

CI

### 1.2.50 show neighbor lac <0-65535>

#### Command

```
show neighbor lac <0-65535>
```

#### Parameters

show

Show running system information

neighbor

Show Handover targets

lac

Handover target cell by LAC

<0-65535>

LAC

### 1.2.51 show neighbor lac-ci <0-65535> <0-65535>

#### Command

```
show neighbor lac-ci <0-65535> <0-65535>
```

#### Parameters

show

Show running system information

neighbor

Show Handover targets

lac-ci

Handover target cell by LAC and CI

<0-65535>

LAC

<0-65535>

CI

### 1.2.52 show nri

#### Command

```
show nri
```

#### Parameters

show

Show running system information

nri

Mapping of Network Resource Indicators to this MSC, for MSC pooling

---

### 1.2.53 show online-help

#### Command

```
show online-help
```

#### Parameters

##### show

Show running system information

##### online-help

Online help

### 1.2.54 show pid

#### Command

```
show pid
```

#### Parameters

##### show

Show running system information

##### pid

Displays the process ID

### 1.2.55 show rate-counters [skip-zero]

#### Command

```
show rate-counters [skip-zero]
```

#### Parameters

##### show

Show running system information

##### rate-counters

Show all rate counters

##### [skip-zero]

Skip items with total count zero

---

### 1.2.56 show sgs-connections

#### Command

```
show sgs-connections
```

#### Parameters

##### show

Show running system information

##### sgs-connections

Show SGs interface connections / MMEs

### 1.2.57 show sms-queue

#### Command

```
show sms-queue
```

#### Parameters

##### show

Show running system information

##### sms-queue

Display SMSQueue statistics

### 1.2.58 show statistics

#### Command

```
show statistics
```

#### Parameters

##### show

Show running system information

##### statistics

Display network statistics

### 1.2.59 show stats [skip-zero]

#### Command

```
show stats [skip-zero]
```

#### Parameters

##### show

Show running system information

##### stats

Show statistical values

##### [skip-zero]

Skip items with total count zero

### 1.2.60 show stats level (global|peer|subscriber) [skip-zero]

#### Command

```
show stats level (global|peer|subscriber) [skip-zero]
```

#### Parameters

##### show

Show running system information

##### stats

Show statistical values

##### level

Set the maximum group level

##### global

Show global groups only

##### peer

Show global and network peer related groups

##### subscriber

Show global, peer, and subscriber groups

##### [skip-zero]

Skip items with total count zero

---

### 1.2.61 show subscriber (msisdn|extension|imsi|tmsi|id) ID [(conn|trans|conn+trans)]

#### Command

```
show subscriber (msisdn|extension|imsi|tmsi|id) ID [(conn|trans|conn+trans)]
```

#### Parameters

##### show

Show running system information

##### subscriber

Operations on a Subscriber

##### msisdn

Identify subscriber by MSISDN (phone number)

##### extension

Legacy alias for 'msisdn'

##### imsi

Identify subscriber by IMSI

##### tmsi

Identify subscriber by TMSI

##### id

Legacy alias for 'imsi'

##### ID

Identifier for the subscriber

##### [conn]

Show child connections

##### [trans]

Show child transactions

##### [conn+trans]

Show child connections and transactions

### 1.2.62 show subscriber cache [(conn|trans|conn+trans)]

#### Command

```
show subscriber cache [(conn|trans|conn+trans)]
```

#### Parameters

##### show

Show running system information

---

subscriber

Show information about subscribers

cache

Display contents of subscriber cache

[conn]

Show child connections

[trans]

Show child transactions

[conn+trans]

Show child connections and transactions

### 1.2.63 show talloc-context (application|global|all) (full|brief|DEPTH)

Command

```
show talloc-context (application|global|all) (full|brief|DEPTH)
```

Parameters

show

Show running system information

talloc-context

Show talloc memory hierarchy

application

Application's context

global

Global context (OTC\_GLOBAL)

all

All contexts, if NULL-context tracking is enabled

full

Display a full talloc memory hierarchy

brief

Display a brief talloc memory hierarchy

DEPTH

Specify required maximal depth value

---

### 1.2.64 show talloc-context (application|global|all) (full|brief|DEPTH) filter REGEXP

#### Command

```
show talloc-context (application|global|all) (full|brief|DEPTH) filter REGEXP
```

#### Parameters

##### show

Show running system information

##### talloc-context

Show talloc memory hierarchy

##### application

Application's context

##### global

Global context (OTC\_GLOBAL)

##### all

All contexts, if NULL-context tracking is enabled

##### full

Display a full talloc memory hierarchy

##### brief

Display a brief talloc memory hierarchy

##### DEPTH

Specify required maximal depth value

##### filter

Filter chunks using regular expression

##### REGEXP

Regular expression

### 1.2.65 show talloc-context (application|global|all) (full|brief|DEPTH) tree ADDRESS

#### Command

```
show talloc-context (application|global|all) (full|brief|DEPTH) tree ADDRESS
```

#### Parameters

##### show

Show running system information

##### talloc-context

Show talloc memory hierarchy

application

Application's context

global

Global context (OTC\_GLOBAL)

all

All contexts, if NULL-context tracking is enabled

full

Display a full talloc memory hierarchy

brief

Display a brief talloc memory hierarchy

DEPTH

Specify required maximal depth value

tree

Display only a specific memory chunk

ADDRESS

Chunk address (e.g. 0xdeadbeef)

### 1.2.66 show timer [(vlr|mgw|mncc|sccp|geran|utran|sgs)] [TNNNN]

Command

```
show timer [(vlr|mgw|mncc|sccp|geran|utran|sgs)] [TNNNN]
```

Parameters

show

Show running system information

timer

Show timers

[vlr]

VLR (Visitors Location Register)

[mgw]

MGW (Media Gateway) interface

[mncc]

MNCC (Mobile Network Call Control) interface

[sccp]

SCCP (Signalling Connection Control Part)

[geran]

GERAN (GSM EDGE Radio Access Network)

---

[utran]

UTRAN (UMTS Terrestrial Radio Access Network)

[sgs]

SGs interface towards MME

[TNNNN]

T- or X-timer-number -- 3GPP compliant timer number of the format '1234' or 'T1234' or 't1234'; Osmocom-specific timer number of the format: 'X1234' or 'x1234'.

### 1.2.67 show transaction

Command

```
show transaction
```

Parameters

show

Show running system information

transaction

Transactions

### 1.2.68 show uptime

Command

```
show uptime
```

Parameters

show

Show running system information

uptime

Displays how long the program has been running

### 1.2.69 show version

Command

```
show version
```

Parameters

show

Show running system information

version

Displays program version

### 1.2.70 sms delete expired

#### Command

```
sms delete expired
```

#### Parameters

sms

SMS related commands

delete

SMS Database related commands

expired

Delete all expired SMS

### 1.2.71 sms send pending

#### Command

```
sms send pending
```

#### Parameters

sms

SMS related commands

send

SMS Sending related commands

pending

Send all pending SMS

### 1.2.72 subscriber (msisdn|extension|imsi|tmsi|id) ID ms-test close-loop (a|b|c|d|e|f|i)

#### Command

```
subscriber (msisdn|extension|imsi|tmsi|id) ID ms-test close-loop (a|b|c|d|e|f|i)
```

#### Parameters

subscriber

Operations on a Subscriber

msisdn

Identify subscriber by MSISDN (phone number)

**extension**

Legacy alias for 'msisdn'

**imsi**

Identify subscriber by IMSI

**tmsi**

Identify subscriber by TMSI

**id**

Legacy alias for 'imsi'

**ID**

Identifier for the subscriber

**ms-test**

Send a TS 04.14 MS Test Command to subscriber

**close-loop**

Close a TCH Loop inside the MS

**a**

Loop Type A

**b**

Loop Type B

**c**

Loop Type C

**d**

Loop Type D

**e**

Loop Type E

**f**

Loop Type F

**i**

Loop Type I

### 1.2.73 subscriber (msisdn|extension|imsi|tmsi|id) ID ms-test open-loop

**Command**

```
subscriber (msisdn|extension|imsi|tmsi|id) ID ms-test open-loop
```

**Parameters****subscriber**

Operations on a Subscriber

msisdn

Identify subscriber by MSISDN (phone number)

extension

Legacy alias for 'msisdn'

imsi

Identify subscriber by IMSI

tmsi

Identify subscriber by TMSI

id

Legacy alias for 'imsi'

ID

Identifier for the subscriber

ms-test

Send a TS 04.14 MS Test Command to subscriber

open-loop

Open a TCH Loop inside the MS

### 1.2.74 subscriber (msisdn|extension|imsi|tmsi|id) ID paging

Command

```
subscriber (msisdn|extension|imsi|tmsi|id) ID paging
```

Parameters

subscriber

Operations on a Subscriber

msisdn

Identify subscriber by MSISDN (phone number)

extension

Legacy alias for 'msisdn'

imsi

Identify subscriber by IMSI

tmsi

Identify subscriber by TMSI

id

Legacy alias for 'imsi'

ID

Identifier for the subscriber

paging

Issue an empty Paging for the subscriber (for debugging)

---

## 1.2.75 subscriber (msisdn|extension|imsi|tmsi|id) ID silent-call start (any|tch/f|tch/h|tch/ ↔ any|sdccch) (signalling|speech-hr|speech-fr|speech-efr|speech-amr) [IP] [<0-65535>]

### Command

```
subscriber (msisdn|extension|imsi|tmsi|id) ID silent-call start (any|tch/f|tch/h|tch/ ↔ any|sdccch) (signalling|speech-hr|speech-fr|speech-efr|speech-amr) [IP] [<0-65535>]
```

### Parameters

#### subscriber

Operations on a Subscriber

#### msisdn

Identify subscriber by MSISDN (phone number)

#### extension

Legacy alias for 'msisdn'

#### imsi

Identify subscriber by IMSI

#### tmsi

Identify subscriber by TMSI

#### id

Legacy alias for 'imsi'

#### ID

Identifier for the subscriber

#### silent-call

Silent call operation

#### start

Start silent call

#### any

Any channel

#### tch/f

TCH/F channel

#### tch/h

TCH/H channel

#### tch/any

Any TCH channel

#### sdccch

SDCCH channel

#### signalling

Signalling only

speech-hr

Speech with HR codec

speech-fr

Speech with FR codec

speech-efr

Speech with EFR codec

speech-amr

Speech with AMR codec

[IP]

Target IP for RTP traffic (default 127.0.0.1)

[<0-65535>]

Target port for RTP traffic (default: 4000)

## 1.2.76 subscriber (msisdn|extension|imsi|tmsi|id) ID silent-call stop

Command

```
subscriber (msisdn|extension|imsi|tmsi|id) ID silent-call stop
```

Parameters

subscriber

Operations on a Subscriber

msisdn

Identify subscriber by MSISDN (phone number)

extension

Legacy alias for 'msisdn'

imsi

Identify subscriber by IMSI

tmsi

Identify subscriber by TMSI

id

Legacy alias for 'imsi'

ID

Identifier for the subscriber

silent-call

Silent call operation

stop

Stop silent call

## 1.2.77 subscriber (msisdn|extension|imsi|tmsi|id) ID silent-sms sender (msisdn|extensio...

### Command

```
subscriber (msisdn|extension|imsi|tmsi|id) ID silent-sms sender (msisdn|extension|imsi| tmsi|id) SENDER_ID send .LINE ↵
```

### Parameters

#### subscriber

Operations on a Subscriber

#### msisdn

Identify subscriber by MSISDN (phone number)

#### extension

Legacy alias for 'msisdn'

#### imsi

Identify subscriber by IMSI

#### tmsi

Identify subscriber by TMSI

#### id

Legacy alias for 'imsi'

#### ID

Identifier for the subscriber

#### silent-sms

Silent SMS Operations

#### sender

Operations on a Subscriber

#### msisdn

Identify subscriber by MSISDN (phone number)

#### extension

Legacy alias for 'msisdn'

#### imsi

Identify subscriber by IMSI

#### tmsi

Identify subscriber by TMSI

#### id

Legacy alias for 'imsi'

#### SENDER\_ID

Identifier for the subscriber

#### send

Send SMS

#### .LINE

Actual SMS Text

## 1.2.78 subscriber (msisdn|extension|imsi|tmsi|id) ID sms sender (msisdn|extension|imsi|...

### Command

```
subscriber (msisdn|extension|imsi|tmsi|id) ID sms sender (msisdn|extension|imsi|tmsi|id ↔  
) SENDER_ID send .LINE
```

### Parameters

#### subscriber

Operations on a Subscriber

#### msisdn

Identify subscriber by MSISDN (phone number)

#### extension

Legacy alias for 'msisdn'

#### imsi

Identify subscriber by IMSI

#### tmsi

Identify subscriber by TMSI

#### id

Legacy alias for 'imsi'

#### ID

Identifier for the subscriber

#### sms

SMS Operations

#### sender

Operations on a Subscriber

#### msisdn

Identify subscriber by MSISDN (phone number)

#### extension

Legacy alias for 'msisdn'

#### imsi

Identify subscriber by IMSI

#### tmsi

Identify subscriber by TMSI

#### id

Legacy alias for 'imsi'

#### SENDER\_ID

Identifier for the subscriber

#### send

Send SMS

#### .LINE

Actual SMS Text

### 1.2.79 subscriber (msisdn|extension|imsi|tmsi|id) ID ussd-notify (0|1|2) .TEXT

#### Command

```
subscriber (msisdn|extension|imsi|tmsi|id) ID ussd-notify (0|1|2) .TEXT
```

#### Parameters

##### subscriber

Operations on a Subscriber

##### msisdn

Identify subscriber by MSISDN (phone number)

##### extension

Legacy alias for 'msisdn'

##### imsi

Identify subscriber by IMSI

##### tmsi

Identify subscriber by TMSI

##### id

Legacy alias for 'imsi'

##### ID

Identifier for the subscriber

##### ussd-notify

Send a USSD notify to the subscriber

##### 0

Alerting Level 0

##### 1

Alerting Level 1

##### 2

Alerting Level 2

##### .TEXT

Text of USSD message to send

### 1.2.80 terminal length <0-512>

#### Command

```
terminal length <0-512>
```

#### Parameters

---

**terminal**

Set terminal line parameters

**length**

Set number of lines on a screen

<0-512>

Number of lines on screen (0 for no pausing)

### 1.2.81 terminal no length

**Command**

```
terminal no length
```

**Parameters****terminal**

Set terminal line parameters

**no**

Negate a command or set its defaults

**length**

Set number of lines on a screen

### 1.2.82 who

**Command**

```
who
```

**Parameters****who**

Display who is on vty

## 1.3 enable

The enable node is a privileged node, allowing to make changes to the configuration and to access further commands like 'configure'. All commands seen on the view node are also available here.

### 1.3.1 configure terminal

#### Command

```
configure terminal
```

#### Parameters

##### configure

Configuration from vty interface

##### terminal

Configuration terminal

### 1.3.2 copy running-config startup-config

#### Command

```
copy running-config startup-config
```

#### Parameters

##### copy

Copy configuration

##### running-config

Copy running config to...

##### startup-config

Copy running config to startup config (same as write file)

### 1.3.3 disable

#### Command

```
disable
```

#### Parameters

##### disable

Turn off privileged mode command

### 1.3.4 logging color (0|1)

#### Command

```
logging color (0|1)
```

#### Parameters

##### logging

Configure logging

##### color

Configure color-printing for log messages

0

Don't use color for printing messages

1

Use color for printing messages

### 1.3.5 logging disable

#### Command

```
logging disable
```

#### Parameters

##### logging

Configure logging

##### disable

Disables logging to this vty

### 1.3.6 logging enable

This command is required to make logging commands available on the telnet VTY.

#### Command

```
logging enable
```

#### Parameters

##### logging

Configure logging

##### enable

Enables logging to this vty

---

### 1.3.7 logging filter all (0|1)

Disable/enable general log output on a given target. Typically, 'logging filter all 1' allows to see the usual log output on a given target. Setting to '0' can be useful when logging to the telnet VTY console: mute all log output to allow typing VTY commands on the telnet prompt without interference from log output; 'logging filter all 1' then re-enables logging in the same log output configuration as before. Some applications provide more specific filters, e.g. to log a given IMSI only. To employ such filters, set 'logging filter all 0' to disable general logging, and then enable a more specific filter instead.

#### Command

```
logging filter all (0|1)
```

#### Parameters

##### logging

Configure logging

##### filter

Filter log messages

##### all

Do you want to log all messages?

##### 0

Only print messages matched by other filters

##### 1

Bypass filter and print all messages

### 1.3.8 logging filter imsi IMSI

#### Command

```
logging filter imsi IMSI
```

#### Parameters

##### logging

Configure logging

##### filter

Filter log messages

##### imsi

Filter log messages by IMSI

##### IMSI

IMSI to be used as filter

---

### 1.3.9 logging level (rll|cc|mm|rr|mncc|pag|msc|mgcp|ho|db|ref|ctrl|smpp|ranap|vlr|iucs...

#### Command

```
logging level (rll|cc|mm|rr|mncc|pag|msc|mgcp|ho|db|ref|ctrl|smpp|ranap|vlr|iucs|bssap| ↵  
sgs|ss|lglobal|llapd|linp|lmux|lmi|lmib|lsms|lctrl|lgtp|lstats|lgsup|loap|lss7| ↵  
lsccp|lsua|lm3ua|lmgcp|ljibuf|lrspro|lns|lbssgp|lnsdata|lnssignal|liuup|lpfcp|lcsn1 ↵  
) (debug|info|notice|error|fatal)
```

#### Parameters

##### logging

Configure logging

##### level

Set the log level for a specified category

##### rll

A-bis Radio Link Layer (RLL)

##### cc

Layer3 Call Control (CC)

##### mm

Layer3 Mobility Management (MM)

##### rr

Layer3 Radio Resource (RR)

##### mncc

MNCC API for Call Control application

##### pag

Paging Subsystem

##### msc

Mobile Switching Center

##### mgcp

Media Gateway Control Protocol

##### ho

Hand-Over

##### db

Database Layer

##### ref

Reference Counting

##### ctrl

Control interface

##### smpp

SMPP interface for external SMS apps

---

ranap  
Radio Access Network Application Part Protocol

vlr  
Visitor Location Register

iucs  
Iu-CS Protocol

bssap  
BSSAP Protocol (A Interface)

sgs  
SGs Interface (SGsAP)

ss  
Supplementary Services

lglobal  
Library-internal global log family

llapd  
LAPD in libosmogsm

linp  
A-bis Input Subsystem

lmux  
A-bis B-Subchannel TRAU Frame Multiplex

lmi  
A-bis Input Driver for Signalling

lmib  
A-bis Input Driver for B-Channels (voice)

lsms  
Layer3 Short Message Service (SMS)

lctrl  
Control Interface

lgtp  
GPRS GTP library

lstats  
Statistics messages and logging

lgsup  
Generic Subscriber Update Protocol

loap  
Osmocom Authentication Protocol

lss7  
libosmo-sigtran Signalling System 7

---

---

lsccp  
libosmo-sigtran SCCP Implementation

lsua  
libosmo-sigtran SCCP User Adaptation

lm3ua  
libosmo-sigtran MTP3 User Adaptation

lmgcp  
libosmo-mgcp Media Gateway Control Protocol

ljibuf  
libosmo-netif Jitter Buffer

lrspro  
Remote SIM protocol

lns  
GPRS NS layer

lbssgp  
GPRS BSSGP layer

lnsdata  
GPRS NS layer data PDU

lnssignal  
GPRS NS layer signal PDU

liuup  
Iu UP layer

lpfcp  
libosmo-pfcp Packet Forwarding Control Protocol

lcsn1  
libosmo-csn1 Concrete Syntax Notation 1 codec

debug  
Log debug messages and higher levels

info  
Log informational messages and higher levels

notice  
Log noticeable messages and higher levels

error  
Log error messages and higher levels

fatal  
Log only fatal messages

---

### 1.3.10 logging level force-all (debug|info|notice|error|fatal)

#### Command

```
logging level force-all (debug|info|notice|error|fatal)
```

#### Parameters

##### logging

Configure logging

##### level

Set the log level for a specified category

##### force-all

Globally force all logging categories to a specific level. This is released by the 'no logging level force-all' command. Note: any 'logging level <category> <level>' commands will have no visible effect after this, until the forced level is released.

##### debug

Log debug messages and higher levels

##### info

Log informational messages and higher levels

##### notice

Log noticeable messages and higher levels

##### error

Log error messages and higher levels

##### fatal

Log only fatal messages

### 1.3.11 logging level set-all (debug|info|notice|error|fatal)

#### Command

```
logging level set-all (debug|info|notice|error|fatal)
```

#### Parameters

##### logging

Configure logging

##### level

Set the log level for a specified category

##### set-all

Once-off set all categories to the given log level. There is no single command to take back these changes -- each category is set to the given level, period.

debug

Log debug messages and higher levels

info

Log informational messages and higher levels

notice

Log noticeable messages and higher levels

error

Log error messages and higher levels

fatal

Log only fatal messages

### 1.3.12 logging print category (0|1)

Command

```
logging print category (0|1)
```

Parameters

logging

Configure logging

print

Log output settings

category

Configure log message

0

Don't prefix each log message

1

Prefix each log message with category/subsystem name

### 1.3.13 logging print category-hex (0|1)

Command

```
logging print category-hex (0|1)
```

Parameters

logging

Configure logging

print

Log output settings

category-hex

Configure log message

0

Don't prefix each log message

1

Prefix each log message with category/subsystem nr in hex ('<000b>')

### 1.3.14 logging print extended-timestamp (0|1)

Command

```
logging print extended-timestamp (0|1)
```

Parameters

logging

Configure logging

print

Log output settings

extended-timestamp

Configure log message timestamping

0

Don't prefix each log message

1

Prefix each log message with current timestamp with YYYYMMDDhhmmssnnn

### 1.3.15 logging print file (0|1|basename) [last]

Command

```
logging print file (0|1|basename) [last]
```

Parameters

logging

Configure logging

print

Log output settings

---

file

Configure log message

0

Don't prefix each log message

1

Prefix each log message with the source file and line

basename

Prefix each log message with the source file's basename (strip leading paths) and line

[last]

Log source file info at the end of a log line. If omitted, log source file info just before the log text.

### 1.3.16 logging print level (0|1)

Command

```
logging print level (0|1)
```

Parameters

logging

Configure logging

print

Log output settings

level

Configure log message

0

Don't prefix each log message

1

Prefix each log message with the log level name

### 1.3.17 logging print thread-id (0|1)

Command

```
logging print thread-id (0|1)
```

Parameters

logging

Configure logging

print

Log output settings

thread-id

Configure log message logging Thread ID

0

Don't prefix each log message

1

Prefix each log message with current Thread ID

### 1.3.18 logging set-log-mask MASK

Command

```
logging set-log-mask MASK
```

Parameters

logging

Configure logging

set-log-mask

Set the logmask of this logging target

MASK

List of logging categories to log, e.g. 'abc:mno:xyz'. Available log categories depend on the specific application, refer to the 'logging level' command. Optionally add individual log levels like 'abc,1:mno,3:xyz,5', where the level numbers are LOGL\_DEBUG=1 LOGL\_INFO=3 LOGL\_NOTICE=5 LOGL\_ERROR=7 LOGL\_FATAL=8

### 1.3.19 logging timestamp (0|1)

Command

```
logging timestamp (0|1)
```

Parameters

logging

Configure logging

timestamp

Configure log message timestamping

0

Don't prefix each log message

1

Prefix each log message with current timestamp

### 1.3.20 logp (rll|cc|mm|rr|mncc|pag|msc|mgcp|ho|db|ref|ctrl|smpp|ranap|vlr|iucs|bssap|sg...

#### Command

```
logp (rll|cc|mm|rr|mncc|pag|msc|mgcp|ho|db|ref|ctrl|smpp|ranap|vlr|iucs|bssap|sgs|ss| ↵
lglobal|llapd|linp|lmux|lmi|lmib|lsms|lctrl|lgtp|lstats|lgsup|loap|lss7|lsccp|lsua| ↵
lm3ua|lmgcp|ljibuf|lrspro|lms|lbssgp|lndata|lnssignal|liuup|lpfcp|lcsn1) (debug| ↵
info|notice|error|fatal) .LOGMESSAGE
```

#### Parameters

##### logp

Print a message on all log outputs; useful for placing markers in test logs

##### rll

A-bis Radio Link Layer (RLL)

##### cc

Layer3 Call Control (CC)

##### mm

Layer3 Mobility Management (MM)

##### rr

Layer3 Radio Resource (RR)

##### mncc

MNCC API for Call Control application

##### pag

Paging Subsystem

##### msc

Mobile Switching Center

##### mgcp

Media Gateway Control Protocol

##### ho

Hand-Over

##### db

Database Layer

##### ref

Reference Counting

##### ctrl

Control interface

##### smpp

SMPP interface for external SMS apps

##### ranap

Radio Access Network Application Part Protocol

---

vlr  
Visitor Location Register

iucs  
Iu-CS Protocol

bssap  
BSSAP Protocol (A Interface)

sgs  
SGs Interface (SGsAP)

ss  
Supplementary Services

lglobal  
Library-internal global log family

llapd  
LAPD in libosmogsm

linp  
A-bis Input Subsystem

lmux  
A-bis B-Subchannel TRAU Frame Multiplex

lmi  
A-bis Input Driver for Signalling

lmib  
A-bis Input Driver for B-Channels (voice)

lsms  
Layer3 Short Message Service (SMS)

lctrl  
Control Interface

lgtp  
GPRS GTP library

lstats  
Statistics messages and logging

lgsup  
Generic Subscriber Update Protocol

loap  
Osmocom Authentication Protocol

lss7  
libosmo-sigtran Signalling System 7

lsccp  
libosmo-sigtran SCCP Implementation

---

---

lsua  
libosmo-sigtran SCCP User Adaptation

lm3ua  
libosmo-sigtran MTP3 User Adaptation

lmgcp  
libosmo-mgcp Media Gateway Control Protocol

ljibuf  
libosmo-netif Jitter Buffer

lrspro  
Remote SIM protocol

lns  
GPRS NS layer

lbssgp  
GPRS BSSGP layer

lnsdata  
GPRS NS layer data PDU

lnssignal  
GPRS NS layer signal PDU

liuup  
Iu UP layer

lpfcp  
libosmo-pfcp Packet Forwarding Control Protocol

lcsn1  
libosmo-csn1 Concrete Syntax Notation 1 codec

debug  
Log debug messages and higher levels

info  
Log informational messages and higher levels

notice  
Log noticeable messages and higher levels

error  
Log error messages and higher levels

fatal  
Log only fatal messages

.LOGMESSAGE  
Arbitrary message to log on given category and log level

---

### 1.3.21 mgw <0-255> block

#### Command

```
mgw <0-255> block
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

mgw

Configure MGCP connection to Media Gateway

<0-255>

reference number

block

block MGCP client so that it won't be used for new calls

### 1.3.22 mgw <0-255> reconnect

#### Command

```
mgw <0-255> reconnect
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

mgw

Configure MGCP connection to Media Gateway

<0-255>

reference number

reconnect

reconfigure and reconnect MGCP client

### 1.3.23 mgw <0-255> unblock

#### Command

```
mgw <0-255> unblock
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

#### mgw

Configure MGCP connection to Media Gateway

#### <0-255>

reference number

#### unblock

unblock MGCP client so that it will be available for new calls

### 1.3.24 no logging level force-all

#### Command

```
no logging level force-all
```

#### Parameters

#### no

Negate a command or set its defaults

#### logging

Configure logging

#### level

Set the log level for a specified category

#### force-all

Release any globally forced log level set with 'logging level force-all <level>'

### 1.3.25 show alarms

#### Command

```
show alarms
```

#### Parameters

#### show

Show running system information

#### alarms

Show current logging configuration

---

### 1.3.26 show asciidoc counters

#### Command

```
show asciidoc counters
```

#### Parameters

##### show

Show running system information

##### asciidoc

Asciidoc generation

##### counters

Generate table of all registered counters

### 1.3.27 show bsc

#### Command

```
show bsc
```

#### Parameters

##### show

Show running system information

##### bsc

BSC

### 1.3.28 show connection [trans]

#### Command

```
show connection [trans]
```

#### Parameters

##### show

Show running system information

##### connection

Subscriber Connections

##### [trans]

Show child transactions of each connection

---

### 1.3.29 show cpu-sched threads

#### Command

```
show cpu-sched threads
```

#### Parameters

##### show

Show running system information

##### cpu-sched

Show Sched section information

##### threads

Show information about running threads)

### 1.3.30 show cs7 (sua|m3ua|ipa) [<0-65534>]

#### Command

```
show cs7 (sua|m3ua|ipa) [<0-65534>]
```

#### Parameters

##### show

Show running system information

##### cs7

ITU-T Signaling System 7

##### sua

SCCP User Adaptation

##### m3ua

MTP3 User Adaptation

##### ipa

IPA Multiplex (SCCP Lite)

##### [<0-65534>]

Port Number

---

### 1.3.31 show cs7 config

#### Command

```
show cs7 config
```

#### Parameters

##### show

Show running system information

##### cs7

ITU-T Signaling System 7

##### config

Currently running cs7 configuration

### 1.3.32 show cs7 instance <0-15> as (active|all|m3ua|sua)

#### Command

```
show cs7 instance <0-15> as (active|all|m3ua|sua)
```

#### Parameters

##### show

Show running system information

##### cs7

ITU-T Signaling System 7

##### instance

An instance of the SS7 stack

##### <0-15>

An instance of the SS7 stack

##### as

Application Server (AS)

##### active

Display all active ASs

##### all

Display all ASs (default)

##### m3ua

Display all m3ua ASs

##### sua

Display all SUA ASs

---

### 1.3.33 show cs7 instance <0-15> asp

#### Command

```
show cs7 instance <0-15> asp
```

#### Parameters

##### show

Show running system information

##### cs7

ITU-T Signaling System 7

##### instance

An instance of the SS7 stack

##### <0-15>

An instance of the SS7 stack

##### asp

Application Server Process (ASP)

### 1.3.34 show cs7 instance <0-15> route

#### Command

```
show cs7 instance <0-15> route
```

#### Parameters

##### show

Show running system information

##### cs7

ITU-T Signaling System 7

##### instance

An instance of the SS7 stack

##### <0-15>

An instance of the SS7 stack

##### route

Routing Table

---

### 1.3.35 show cs7 instance <0-15> sccp addressbook

#### Command

```
show cs7 instance <0-15> sccp addressbook
```

#### Parameters

show

Show running system information

cs7

ITU-T Signaling System 7

instance

An instance of the SS7 stack

<0-15>

An instance of the SS7 stack

sccp

Signalling Connection Control Part

addressbook

List all SCCP addressbook entries

### 1.3.36 show cs7 instance <0-15> sccp connections

#### Command

```
show cs7 instance <0-15> sccp connections
```

#### Parameters

show

Show running system information

cs7

ITU-T Signaling System 7

instance

An instance of the SS7 stack

<0-15>

An instance of the SS7 stack

sccp

Signalling Connection Control Part

connections

Show List of active SCCP connections

---

### 1.3.37 show cs7 instance <0-15> sccp ssn <0-65535>

#### Command

```
show cs7 instance <0-15> sccp ssn <0-65535>
```

#### Parameters

show

Show running system information

cs7

ITU-T Signaling System 7

instance

An instance of the SS7 stack

<0-15>

An instance of the SS7 stack

sccp

Signalling Connection Control Part

ssn

Find an SCCP User registered for the given SSN

<0-65535>

Subsystem Number (SSN)

### 1.3.38 show cs7 instance <0-15> sccp timers

#### Command

```
show cs7 instance <0-15> sccp timers
```

#### Parameters

show

Show running system information

cs7

ITU-T Signaling System 7

instance

An instance of the SS7 stack

<0-15>

An instance of the SS7 stack

sccp

Signaling Connection Control Part

timers

Show List of SCCP timers

### 1.3.39 show cs7 instance <0-15> sccp users

#### Command

```
show cs7 instance <0-15> sccp users
```

#### Parameters

##### show

Show running system information

##### cs7

ITU-T Signaling System 7

##### instance

An instance of the SS7 stack

##### <0-15>

An instance of the SS7 stack

##### sccp

Signalling Connection Control Part

##### users

Show List of SCCP Users registered

### 1.3.40 show cs7 instance <0-15> users

#### Command

```
show cs7 instance <0-15> users
```

#### Parameters

##### show

Show running system information

##### cs7

ITU-T Signaling System 7

##### instance

An instance of the SS7 stack

##### <0-15>

An instance of the SS7 stack

##### users

User Table

---

### 1.3.41 show fsm NAME

#### Command

```
show fsm NAME
```

#### Parameters

##### show

Show running system information

##### fsm

Show information about finite state machines

##### NAME

Display information about a single named finite state machine

### 1.3.42 show fsm all

#### Command

```
show fsm all
```

#### Parameters

##### show

Show running system information

##### fsm

Show information about finite state machines

##### all

Display a list of all registered finite state machines

### 1.3.43 show fsm-instances NAME

#### Command

```
show fsm-instances NAME
```

#### Parameters

##### show

Show running system information

##### fsm-instances

Show information about finite state machine instances

##### NAME

Display a list of all FSM instances of the named finite state machine

---

### 1.3.44 show fsm-instances all

#### Command

```
show fsm-instances all
```

#### Parameters

##### show

Show running system information

##### fsm-instances

Show information about finite state machine instances

##### all

Display a list of all FSM instances of all finite state machine

### 1.3.45 show history

#### Command

```
show history
```

#### Parameters

##### show

Show running system information

##### history

Display the session command history

### 1.3.46 show logging vty

#### Command

```
show logging vty
```

#### Parameters

##### show

Show running system information

##### logging

Show current logging configuration

##### vtty

Show current logging configuration for this vty

---

### 1.3.47 show mgw-pool

#### Command

```
show mgw-pool
```

#### Parameters

##### show

Show running system information

##### mgw-pool

Display information about the MGW-Pool

### 1.3.48 show neighbor

#### Command

```
show neighbor
```

#### Parameters

##### show

Show running system information

##### neighbor

Show Handover targets

### 1.3.49 show neighbor (a|iu)

#### Command

```
show neighbor (a|iu)
```

#### Parameters

##### show

Show running system information

##### neighbor

Show Handover targets

##### a

Neighbor on GERAN-A

##### iu

Neighbor on UTRAN-Iu

### 1.3.50 **show neighbor (a|iu) (ran-pc|msc-ipa-name) RAN\_PC\_OR\_MSC\_IPA\_NAME**

#### Command

```
show neighbor (a|iu) (ran-pc|msc-ipa-name) RAN_PC_OR_MSC_IPA_NAME
```

#### Parameters

##### show

Show running system information

##### neighbor

Show Handover targets

##### a

Neighbor on GERAN-A

##### iu

Neighbor on UTRAN-Iu

##### ran-pc

SCCP point code of RAN peer

##### msc-ipa-name

GSUP IPA name of target MSC

##### RAN\_PC\_OR\_MSC\_IPA\_NAME

Point code or MSC IPA name value

### 1.3.51 **show neighbor (a|iu) cgi <0-999> <0-999> <0-65535> <0-65535>**

#### Command

```
show neighbor (a|iu) cgi <0-999> <0-999> <0-65535> <0-65535>
```

#### Parameters

##### show

Show running system information

##### neighbor

Show Handover targets

##### a

Neighbor on GERAN-A

##### iu

Neighbor on UTRAN-Iu

##### cgi

Handover target cell by Cell-Global Identifier (MCC, MNC, LAC, CI)

---

<0-999>

MCC

<0-999>

MNC

<0-65535>

LAC

<0-65535>

CI

### 1.3.52 show neighbor (a|iu) lac <0-65535>

Command

```
show neighbor (a|iu) lac <0-65535>
```

Parameters

show

Show running system information

neighbor

Show Handover targets

a

Neighbor on GERAN-A

iu

Neighbor on UTRAN-Iu

lac

Handover target cell by LAC

<0-65535>

LAC

### 1.3.53 show neighbor (a|iu) lac-ci <0-65535> <0-65535>

Command

```
show neighbor (a|iu) lac-ci <0-65535> <0-65535>
```

Parameters

show

Show running system information

neighbor

Show Handover targets

a

Neighbor on GERAN-A

iu

Neighbor on UTRAN-Iu

lac-ci

Handover target cell by LAC and CI

<0-65535>

LAC

<0-65535>

CI

### 1.3.54 show neighbor cgi <0-999> <0-999> <0-65535> <0-65535>

Command

```
show neighbor cgi <0-999> <0-999> <0-65535> <0-65535>
```

Parameters

show

Show running system information

neighbor

Show Handover targets

cgi

Handover target cell by Cell-Global Identifier (MCC, MNC, LAC, CI)

<0-999>

MCC

<0-999>

MNC

<0-65535>

LAC

<0-65535>

CI

### 1.3.55 show neighbor lac <0-65535>

#### Command

```
show neighbor lac <0-65535>
```

#### Parameters

##### show

Show running system information

##### neighbor

Show Handover targets

##### lac

Handover target cell by LAC

<0-65535>

LAC

### 1.3.56 show neighbor lac-ci <0-65535> <0-65535>

#### Command

```
show neighbor lac-ci <0-65535> <0-65535>
```

#### Parameters

##### show

Show running system information

##### neighbor

Show Handover targets

##### lac-ci

Handover target cell by LAC and CI

<0-65535>

LAC

<0-65535>

CI

### 1.3.57 show nri

#### Command

```
show nri
```

#### Parameters

##### show

Show running system information

##### nri

Mapping of Network Resource Indicators to this MSC, for MSC pooling

---

### 1.3.58 show online-help

#### Command

```
show online-help
```

#### Parameters

##### show

Show running system information

##### online-help

Online help

### 1.3.59 show rate-counters [skip-zero]

#### Command

```
show rate-counters [skip-zero]
```

#### Parameters

##### show

Show running system information

##### rate-counters

Show all rate counters

##### [skip-zero]

Skip items with total count zero

### 1.3.60 show sgs-connections

#### Command

```
show sgs-connections
```

#### Parameters

##### show

Show running system information

##### sgs-connections

Show SGs interface connections / MMEs

---

### 1.3.61 show sms-queue

#### Command

```
show sms-queue
```

#### Parameters

##### show

Show running system information

##### sms-queue

Display SMSQueue statistics

### 1.3.62 show startup-config

#### Command

```
show startup-config
```

#### Parameters

##### show

Show running system information

##### startup-config

Contentes of startup configuration

### 1.3.63 show statistics

#### Command

```
show statistics
```

#### Parameters

##### show

Show running system information

##### statistics

Display network statistics

### 1.3.64 show stats [skip-zero]

#### Command

```
show stats [skip-zero]
```

#### Parameters

##### show

Show running system information

##### stats

Show statistical values

##### [skip-zero]

Skip items with total count zero

### 1.3.65 show stats level (global|peer|subscriber) [skip-zero]

#### Command

```
show stats level (global|peer|subscriber) [skip-zero]
```

#### Parameters

##### show

Show running system information

##### stats

Show statistical values

##### level

Set the maximum group level

##### global

Show global groups only

##### peer

Show global and network peer related groups

##### subscriber

Show global, peer, and subscriber groups

##### [skip-zero]

Skip items with total count zero

---

### 1.3.66 show subscriber (msisdn|extension|imsi|tmsi|id) ID [(conn|trans|conn+trans)]

#### Command

```
show subscriber (msisdn|extension|imsi|tmsi|id) ID [(conn|trans|conn+trans)]
```

#### Parameters

##### show

Show running system information

##### subscriber

Operations on a Subscriber

##### msisdn

Identify subscriber by MSISDN (phone number)

##### extension

Legacy alias for 'msisdn'

##### imsi

Identify subscriber by IMSI

##### tmsi

Identify subscriber by TMSI

##### id

Legacy alias for 'imsi'

##### ID

Identifier for the subscriber

##### [conn]

Show child connections

##### [trans]

Show child transactions

##### [conn+trans]

Show child connections and transactions

### 1.3.67 show subscriber cache [(conn|trans|conn+trans)]

#### Command

```
show subscriber cache [(conn|trans|conn+trans)]
```

#### Parameters

##### show

Show running system information

---

subscriber

Show information about subscribers

cache

Display contents of subscriber cache

[conn]

Show child connections

[trans]

Show child transactions

[conn+trans]

Show child connections and transactions

### 1.3.68 show talloc-context (application|global|all) (full|brief|DEPTH)

Command

```
show talloc-context (application|global|all) (full|brief|DEPTH)
```

Parameters

show

Show running system information

talloc-context

Show talloc memory hierarchy

application

Application's context

global

Global context (OTC\_GLOBAL)

all

All contexts, if NULL-context tracking is enabled

full

Display a full talloc memory hierarchy

brief

Display a brief talloc memory hierarchy

DEPTH

Specify required maximal depth value

### 1.3.69 show talloc-context (application|global|all) (full|brief|DEPTH) filter REGEXP

#### Command

```
show talloc-context (application|global|all) (full|brief|DEPTH) filter REGEXP
```

#### Parameters

##### show

Show running system information

##### talloc-context

Show talloc memory hierarchy

##### application

Application's context

##### global

Global context (OTC\_GLOBAL)

##### all

All contexts, if NULL-context tracking is enabled

##### full

Display a full talloc memory hierarchy

##### brief

Display a brief talloc memory hierarchy

##### DEPTH

Specify required maximal depth value

##### filter

Filter chunks using regular expression

##### REGEXP

Regular expression

### 1.3.70 show talloc-context (application|global|all) (full|brief|DEPTH) tree ADDRESS

#### Command

```
show talloc-context (application|global|all) (full|brief|DEPTH) tree ADDRESS
```

#### Parameters

##### show

Show running system information

##### talloc-context

Show talloc memory hierarchy

application

Application's context

global

Global context (OTC\_GLOBAL)

all

All contexts, if NULL-context tracking is enabled

full

Display a full talloc memory hierarchy

brief

Display a brief talloc memory hierarchy

DEPTH

Specify required maximal depth value

tree

Display only a specific memory chunk

ADDRESS

Chunk address (e.g. 0xdeadbeef)

### 1.3.71 **show timer [(vlr|mgw|mncc|sccp|geran|utran|sgs)] [TNNNN]**

Command

```
show timer [(vlr|mgw|mncc|sccp|geran|utran|sgs)] [TNNNN]
```

Parameters

show

Show running system information

timer

Show timers

[vlr]

VLR (Visitors Location Register)

[mgw]

MGW (Media Gateway) interface

[mncc]

MNCC (Mobile Network Call Control) interface

[sccp]

SCCP (Signalling Connection Control Part)

[geran]

GERAN (GSM EDGE Radio Access Network)

[utran]

UTRAN (UMTS Terrestrial Radio Access Network)

[sgs]

SGs interface towards MME

[TNNNN]

T- or X-timer-number -- 3GPP compliant timer number of the format '1234' or 'T1234' or 't1234'; Osmocom-specific timer number of the format: 'X1234' or 'x1234'.

### 1.3.72 show transaction

Command

```
show transaction
```

Parameters

show

Show running system information

transaction

Transactions

### 1.3.73 show version

Command

```
show version
```

Parameters

show

Show running system information

version

Displays program version

### 1.3.74 shutdown

Command

```
shutdown
```

Parameters

shutdown

Request a shutdown of the program

---

### 1.3.75 sms delete expired

#### Command

```
sms delete expired
```

#### Parameters

sms

SMS related commands

delete

SMS Database related commands

expired

Delete all expired SMS

### 1.3.76 sms send pending

#### Command

```
sms send pending
```

#### Parameters

sms

SMS related commands

send

SMS Sending related commands

pending

Send all pending SMS

### 1.3.77 sms-queue clear

#### Command

```
sms-queue clear
```

#### Parameters

sms-queue

SMS Queue

clear

Clear the queue of pending SMS

### 1.3.78 sms-queue max-failure <1-500>

#### Command

```
sms-queue max-failure <1-500>
```

#### Parameters

sms-queue

SMS Queue

max-failure

Maximum amount of delivery failures

<1-500>

Amount

### 1.3.79 sms-queue max-pending <1-500>

#### Command

```
sms-queue max-pending <1-500>
```

#### Parameters

sms-queue

SMS Queue

max-pending

SMS to deliver in parallel

<1-500>

Amount

### 1.3.80 sms-queue trigger

#### Command

```
sms-queue trigger
```

#### Parameters

sms-queue

SMS Queue

trigger

Trigger sending messages

---

### 1.3.81 stats report

#### Command

```
stats report
```

#### Parameters

stats

Stats related commands

report

Manurally trigger reporting of stats

### 1.3.82 stats reset

#### Command

```
stats reset
```

#### Parameters

stats

Stats related commands

reset

Reset all rate counter stats

### 1.3.83 subscriber (msisdn|extension|imsi|tmsi|id) ID expire

#### Command

```
subscriber (msisdn|extension|imsi|tmsi|id) ID expire
```

#### Parameters

subscriber

Operations on a Subscriber

msisdn

Identify subscriber by MSISDN (phone number)

extension

Legacy alias for 'msisdn'

imsi

Identify subscriber by IMSI

---

tmsi

Identify subscriber by TMSI

id

Legacy alias for 'imsi'

ID

Identifier for the subscriber

expire

Expire the subscriber Now

### 1.3.84 subscriber (msisdn|extension|imsi|tmsi|id) ID ms-test close-loop (a|b|c|d|e|f|i)

Command

```
subscriber (msisdn|extension|imsi|tmsi|id) ID ms-test close-loop (a|b|c|d|e|f|i)
```

Parameters

subscriber

Operations on a Subscriber

msisdn

Identify subscriber by MSISDN (phone number)

extension

Legacy alias for 'msisdn'

imsi

Identify subscriber by IMSI

tmsi

Identify subscriber by TMSI

id

Legacy alias for 'imsi'

ID

Identifier for the subscriber

ms-test

Send a TS 04.14 MS Test Command to subscriber

close-loop

Close a TCH Loop inside the MS

a

Loop Type A

b

Loop Type B

- c  
Loop Type C
- d  
Loop Type D
- e  
Loop Type E
- f  
Loop Type F
- i  
Loop Type I

### 1.3.85 subscriber (msisdn|extension|imsi|tmsi|id) ID ms-test open-loop

#### Command

```
subscriber (msisdn|extension|imsi|tmsi|id) ID ms-test open-loop
```

#### Parameters

##### subscriber

Operations on a Subscriber

##### msisdn

Identify subscriber by MSISDN (phone number)

##### extension

Legacy alias for 'msisdn'

##### imsi

Identify subscriber by IMSI

##### tmsi

Identify subscriber by TMSI

##### id

Legacy alias for 'imsi'

##### ID

Identifier for the subscriber

##### ms-test

Send a TS 04.14 MS Test Command to subscriber

##### open-loop

Open a TCH Loop inside the MS

### 1.3.86 subscriber (msisdn|extension|imsi|tmsi|id) ID paging

#### Command

```
subscriber (msisdn|extension|imsi|tmsi|id) ID paging
```

#### Parameters

##### subscriber

Operations on a Subscriber

##### msisdn

Identify subscriber by MSISDN (phone number)

##### extension

Legacy alias for 'msisdn'

##### imsi

Identify subscriber by IMSI

##### tmsi

Identify subscriber by TMSI

##### id

Legacy alias for 'imsi'

##### ID

Identifier for the subscriber

##### paging

Issue an empty Paging for the subscriber (for debugging)

### 1.3.87 subscriber (msisdn|extension|imsi|tmsi|id) ID silent-call start (any|tch/f|tch/h...

#### Command

```
subscriber (msisdn|extension|imsi|tmsi|id) ID silent-call start (any|tch/f|tch/h|tch/ ↔  
any|sdccch) (signalling|speech-hr|speech-fr|speech-efr|speech-amr) [IP] [<0-65535>]
```

#### Parameters

##### subscriber

Operations on a Subscriber

##### msisdn

Identify subscriber by MSISDN (phone number)

##### extension

Legacy alias for 'msisdn'

##### imsi

Identify subscriber by IMSI

---

tmsi  
Identify subscriber by TMSI

id  
Legacy alias for 'imsi'

ID  
Identifier for the subscriber

silent-call  
Silent call operation

start  
Start silent call

any  
Any channel

tch/f  
TCH/F channel

tch/h  
TCH/H channel

tch/any  
Any TCH channel

sdccch  
SDCCH channel

signalling  
Signalling only

speech-hr  
Speech with HR codec

speech-fr  
Speech with FR codec

speech-efr  
Speech with EFR codec

speech-amr  
Speech with AMR codec

[IP]  
Target IP for RTP traffic (default 127.0.0.1)

[<0-65535>]  
Target port for RTP traffic (default: 4000)

---

### 1.3.88 subscriber (msisdn|extension|imsi|tmsi|id) ID silent-call stop

#### Command

```
subscriber (msisdn|extension|imsi|tmsi|id) ID silent-call stop
```

#### Parameters

##### subscriber

Operations on a Subscriber

##### msisdn

Identify subscriber by MSISDN (phone number)

##### extension

Legacy alias for 'msisdn'

##### imsi

Identify subscriber by IMSI

##### tmsi

Identify subscriber by TMSI

##### id

Legacy alias for 'imsi'

##### ID

Identifier for the subscriber

##### silent-call

Silent call operation

##### stop

Stop silent call

### 1.3.89 subscriber (msisdn|extension|imsi|tmsi|id) ID silent-sms sender (msisdn|extension...

#### Command

```
subscriber (msisdn|extension|imsi|tmsi|id) ID silent-sms sender (msisdn|extension|imsi| ↔  
tmsi|id) SENDER_ID send .LINE
```

#### Parameters

##### subscriber

Operations on a Subscriber

##### msisdn

Identify subscriber by MSISDN (phone number)

##### extension

Legacy alias for 'msisdn'

imsi

Identify subscriber by IMSI

tmsi

Identify subscriber by TMSI

id

Legacy alias for 'imsi'

ID

Identifier for the subscriber

silent-sms

Silent SMS Operations

sender

Operations on a Subscriber

msisdn

Identify subscriber by MSISDN (phone number)

extension

Legacy alias for 'msisdn'

imsi

Identify subscriber by IMSI

tmsi

Identify subscriber by TMSI

id

Legacy alias for 'imsi'

SENDER\_ID

Identifier for the subscriber

send

Send SMS

.LINE

Actual SMS Text

### 1.3.90 subscriber (msisdn|extension|imsi|tmsi|id) ID sms delete-all

Command

```
subscriber (msisdn|extension|imsi|tmsi|id) ID sms delete-all
```

Parameters

subscriber

Operations on a Subscriber

msisdn

Identify subscriber by MSISDN (phone number)

extension

Legacy alias for 'msisdn'

imsi

Identify subscriber by IMSI

tmsi

Identify subscriber by TMSI

id

Legacy alias for 'imsi'

ID

Identifier for the subscriber

sms

SMS Operations

delete-all

Delete all SMS to be delivered to this subscriber -- WARNING: the SMS data for all unsent SMS for this subscriber WILL BE LOST.

### 1.3.91 subscriber (msisdn|extension|imsi|tmsi|id) ID sms pending-send

Command

```
subscriber (msisdn|extension|imsi|tmsi|id) ID sms pending-send
```

Parameters

subscriber

Operations on a Subscriber

msisdn

Identify subscriber by MSISDN (phone number)

extension

Legacy alias for 'msisdn'

imsi

Identify subscriber by IMSI

tmsi

Identify subscriber by TMSI

id

Legacy alias for 'imsi'

ID

Identifier for the subscriber

sms

SMS Operations

pending-send

Send pending SMS

### 1.3.92 subscriber (msisdn|extension|imsi|tmsi|id) ID sms sender (msisdn|extension|imsi|...

#### Command

```
subscriber (msisdn|extension|imsi|tmsi|id) ID sms sender (msisdn|extension|imsi|tmsi|id ↔  
) SENDER_ID send .LINE
```

#### Parameters

##### subscriber

Operations on a Subscriber

##### msisdn

Identify subscriber by MSISDN (phone number)

##### extension

Legacy alias for 'msisdn'

##### imsi

Identify subscriber by IMSI

##### tmsi

Identify subscriber by TMSI

##### id

Legacy alias for 'imsi'

##### ID

Identifier for the subscriber

##### sms

SMS Operations

##### sender

Operations on a Subscriber

##### msisdn

Identify subscriber by MSISDN (phone number)

##### extension

Legacy alias for 'msisdn'

##### imsi

Identify subscriber by IMSI

##### tmsi

Identify subscriber by TMSI

##### id

Legacy alias for 'imsi'

##### SENDER\_ID

Identifier for the subscriber

##### send

Send SMS

##### .LINE

Actual SMS Text

### 1.3.93 subscriber (msisdn|extension|imsi|tmsi|id) ID ussd-notify (0|1|2) .TEXT

#### Command

```
subscriber (msisdn|extension|imsi|tmsi|id) ID ussd-notify (0|1|2) .TEXT
```

#### Parameters

##### subscriber

Operations on a Subscriber

##### msisdn

Identify subscriber by MSISDN (phone number)

##### extension

Legacy alias for 'msisdn'

##### imsi

Identify subscriber by IMSI

##### tmsi

Identify subscriber by TMSI

##### id

Legacy alias for 'imsi'

##### ID

Identifier for the subscriber

##### ussd-notify

Send a USSD notify to the subscriber

##### 0

Alerting Level 0

##### 1

Alerting Level 1

##### 2

Alerting Level 2

##### .TEXT

Text of USSD message to send

### 1.3.94 terminal length <0-512>

#### Command

```
terminal length <0-512>
```

#### Parameters

---

terminal

Set terminal line parameters

length

Set number of lines on a screen

<0-512>

Number of lines on screen (0 for no pausing)

### 1.3.95 terminal monitor

Command

```
terminal monitor
```

Parameters

terminal

Set terminal line parameters

monitor

Copy debug output to the current terminal line

### 1.3.96 terminal no length

Command

```
terminal no length
```

Parameters

terminal

Set terminal line parameters

no

Negate a command or set its defaults

length

Set number of lines on a screen

### 1.3.97 terminal no monitor

#### Command

```
terminal no monitor
```

#### Parameters

##### terminal

Set terminal line parameters

##### no

Negate a command or set its defaults

##### monitor

Copy debug output to the current terminal line

### 1.3.98 who

#### Command

```
who
```

#### Parameters

##### who

Display who is on vty

## 1.4 config

The config node is the root for all configuration commands, which are identical to the config file format. Changes made on the telnet VTY can be made persistent with the 'write file' command.

### 1.4.1 banner motd default

#### Command

```
banner motd default
```

#### Parameters

##### banner

Set banner string

##### motd

Strings for motd

##### default

Default string

---

### 1.4.2 banner motd file [FILE]

#### Command

```
banner motd file [FILE]
```

#### Parameters

banner

Set banner

motd

Banner for motd

file

Banner from a file

[FILE]

Filename

### 1.4.3 cpu-sched

#### Command

```
cpu-sched
```

#### Parameters

cpu-sched

Configure CPU Scheduler related settings

### 1.4.4 cs7 instance <0-15>

#### Command

```
cs7 instance <0-15>
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

cs7

ITU-T Signaling System 7

instance

Configure a SS7 Instance

<0-15>

An instance of the SS7 stack

### 1.4.5 ctrl

#### Command

```
ctrl
```

#### Parameters

ctrl

Configure the Control Interface

### 1.4.6 enable password (8|) WORD

#### Command

```
enable password (8|) WORD
```

#### Parameters

enable

Modify enable password parameters

password

Assign the privileged level password

8

Specifies a HIDDEN password will follow

dummy string

WORD

The HIDDEN 'enable' password string

### 1.4.7 enable password LINE

#### Command

```
enable password LINE
```

#### Parameters

enable

Modify enable password parameters

password

Assign the privileged level password

LINE

The UNENCRYPTED (cleartext) 'enable' password

---

### 1.4.8 hlr

#### Command

```
hlr
```

#### Parameters

hlr

Configure connection to the HLR

### 1.4.9 hostname WORD

#### Command

```
hostname WORD
```

#### Parameters

hostname

Set system's network name

WORD

This system's network name

### 1.4.10 line vty

#### Command

```
line vty
```

#### Parameters

line

Configure a terminal line

vtty

Virtual terminal

### 1.4.11 log alarms <2-32700>

#### Command

```
log alarms <2-32700>
```

#### Parameters

log

Configure logging sub-system

alarms

Logging alarms to osmo\_strrb

<2-32700>

Maximum number of messages to log

### 1.4.12 log file FILENAME [blocking-io]

#### Command

```
log file FILENAME [blocking-io]
```

#### Parameters

log

Configure logging sub-system

file

Logging to text file

FILENAME

Filename

[blocking-io]

Use blocking, synchronous I/O

### 1.4.13 log gsmtap [HOSTNAME]

#### Command

```
log gsmtap [HOSTNAME]
```

#### Parameters

log

Configure logging sub-system

gsmtap

Logging via GSMTAP

[HOSTNAME]

Host name to send the GSMTAP logging to (UDP port 4729)

---

### 1.4.14 log stderr [blocking-io]

#### Command

```
log stderr [blocking-io]
```

#### Parameters

log

Configure logging sub-system

stderr

Logging via STDERR of the process

[blocking-io]

Use blocking, synchronous I/O

### 1.4.15 log syslog (authpriv|cron|daemon|ftp|lpr|mail|news|user|uucp)

#### Command

```
log syslog (authpriv|cron|daemon|ftp|lpr|mail|news|user|uucp)
```

#### Parameters

log

Configure logging sub-system

syslog

Logging via syslog

authpriv

Security/authorization messages facility

cron

Clock daemon (cron/at) facility

daemon

General system daemon facility

ftp

Ftp daemon facility

lpr

Line printer facility

mail

Mail facility

news

News facility

user

Generic facility

uucp

UUCP facility

---

### 1.4.16 log syslog local <0-7>

#### Command

```
log syslog local <0-7>
```

#### Parameters

log

Configure logging sub-system

syslog

Logging via syslog

local

Syslog LOCAL facility

<0-7>

Local facility number

### 1.4.17 log systemd-journal [raw]

#### Command

```
log systemd-journal [raw]
```

#### Parameters

log

Configure logging sub-system

systemd-journal

Logging to systemd-journal

[raw]

Offload rendering of the meta information (location, category) to systemd

### 1.4.18 mncc-int

#### Command

```
mncc-int
```

#### Parameters

mncc-int

Configure internal MNCC handler

---

### 1.4.19 msc

#### Command

```
msc
```

#### Parameters

msc

Configure MSC options

### 1.4.20 network

#### Command

```
network
```

#### Parameters

network

Configure the GSM network

### 1.4.21 no banner motd

#### Command

```
no banner motd
```

#### Parameters

no

Negate a command or set its defaults

banner

Set banner string

motd

Strings for motd

### 1.4.22 no enable password

#### Command

```
no enable password
```

#### Parameters

no

Negate a command or set its defaults

enable

Modify enable password parameters

password

Assign the privileged level password

### 1.4.23 no hostname [HOSTNAME]

#### Command

```
no hostname [HOSTNAME]
```

#### Parameters

no

Negate a command or set its defaults

hostname

Reset system's network name

[HOSTNAME]

Host name of this router

### 1.4.24 no log alarms

#### Command

```
no log alarms
```

#### Parameters

no

Negate a command or set its defaults

log

Configure logging sub-system

alarms

Logging alarms to osmo\_strrb

### 1.4.25 no log file FILENAME

#### Command

```
no log file FILENAME
```

#### Parameters

no

Negate a command or set its defaults

log

Configure logging sub-system

file

Logging to text file

FILENAME

Filename

### 1.4.26 no log gsmtap [HOSTNAME]

#### Command

```
no log gsmtap [HOSTNAME]
```

#### Parameters

no

Negate a command or set its defaults

log

Configure logging sub-system

gsmtap

Logging via GSMTAP

[HOSTNAME]

Host name to send the GSMTAP logging to (UDP port 4729)

### 1.4.27 no log stderr

#### Command

```
no log stderr
```

#### Parameters

no

Negate a command or set its defaults

log

Configure logging sub-system

stderr

Logging via STDERR of the process

---

### 1.4.28 no log syslog

#### Command

```
no log syslog
```

#### Parameters

no

Negate a command or set its defaults

log

Configure logging sub-system

syslog

Logging via syslog

### 1.4.29 no log systemd-journal

#### Command

```
no log systemd-journal
```

#### Parameters

no

Negate a command or set its defaults

log

Configure logging sub-system

systemd-journal

Logging to systemd-journal

### 1.4.30 no service advanced-vty

#### Command

```
no service advanced-vty
```

#### Parameters

no

Negate a command or set its defaults

service

Set up miscellaneous service

advanced-vty

Enable advanced mode vty interface

---

### 1.4.31 no service terminal-length [<0-512>]

#### Command

```
no service terminal-length [<0-512>]
```

#### Parameters

no

Negate a command or set its defaults

service

Set up miscellaneous service

terminal-length

System wide terminal length configuration

[<0-512>]

Number of lines of VTY (0 means no line control)

### 1.4.32 no stats reporter log [NAME]

#### Command

```
no stats reporter log [NAME]
```

#### Parameters

no

Negate a command or set its defaults

stats

Configure stats sub-system

reporter

Configure a stats reporter

log

Report to the logger

[NAME]

Name of the reporter

### 1.4.33 no stats reporter statsd [NAME]

#### Command

```
no stats reporter statsd [NAME]
```

#### Parameters

no

Negate a command or set its defaults

stats

Configure stats sub-system

reporter

Configure a stats reporter

statsd

Report to a STATSD server

[NAME]

Name of the reporter

### 1.4.34 password (8|) WORD

#### Command

```
password (8|) WORD
```

#### Parameters

password

Assign the terminal connection password

8

Specifies a HIDDEN password will follow

dummy string

WORD

The HIDDEN line password string

### 1.4.35 password LINE

#### Command

```
password LINE
```

#### Parameters

password

Assign the terminal connection password

LINE

The UNENCRYPTED (cleartext) line password

### 1.4.36 service advanced-vty

#### Command

```
service advanced-vty
```

#### Parameters

##### service

Set up miscellaneous service

##### advanced-vty

Enable advanced mode vty interface

### 1.4.37 service terminal-length <0-512>

#### Command

```
service terminal-length <0-512>
```

#### Parameters

##### service

Set up miscellaneous service

##### terminal-length

System wide terminal length configuration

##### <0-512>

Number of lines of VTY (0 means no line control)

### 1.4.38 sgs

#### Command

```
sgs
```

#### Parameters

##### sgs

Configure the SGs interface

### 1.4.39 show history

#### Command

```
show history
```

#### Parameters

##### show

Show running system information

##### history

Display the session command history

### 1.4.40 smsc

#### Command

```
smsc
```

#### Parameters

##### smsc

Configure SMSC options

### 1.4.41 stats interval <0-65535>

#### Command

```
stats interval <0-65535>
```

#### Parameters

##### stats

Configure stats sub-system

##### interval

Set the reporting interval

##### <0-65535>

Interval in seconds (0 disables the reporting interval)

---

### 1.4.42 stats reporter log [NAME]

#### Command

```
stats reporter log [NAME]
```

#### Parameters

stats

Configure stats sub-system

reporter

Configure a stats reporter

log

Report to the logger

[NAME]

Name of the reporter

### 1.4.43 stats reporter statsd [NAME]

#### Command

```
stats reporter statsd [NAME]
```

#### Parameters

stats

Configure stats sub-system

reporter

Configure a stats reporter

statsd

Report to a STATSD server

[NAME]

Name of the reporter

### 1.4.44 stats-tcp batch-size <1-65535>

#### Command

```
stats-tcp batch-size <1-65535>
```

#### Parameters

stats-tcp

Configure stats sub-system

batch-size

Set the number of tcp sockets that are processed per stats polling interval

<1-65535>

Number of sockets per interval

### 1.4.45 stats-tcp interval <0-65535>

#### Command

```
stats-tcp interval <0-65535>
```

#### Parameters

##### stats-tcp

Configure stats sub-system

##### interval

Set the tcp socket stats polling interval

##### <0-65535>

Interval in seconds (0 disables the polling interval)

## 1.5 config-log

The log node is commonly available in all Osmocom programs and allows configuring logging to stderr and/or log files, including logging category and level filtering as well as output formatting options. Note that the 'logging enable' command is required to make logging commands available on the telnet VTY.

### 1.5.1 logging color (0|1)

#### Command

```
logging color (0|1)
```

#### Parameters

##### logging

Configure logging

##### color

Configure color-printing for log messages

##### 0

Don't use color for printing messages

##### 1

Use color for printing messages

---

### 1.5.2 logging filter all (0|1)

Disable/enable general log output on a given target. Typically, 'logging filter all 1' allows to see the usual log output on a given target. Setting to '0' can be useful when logging to the telnet VTY console: mute all log output to allow typing VTY commands on the telnet prompt without interference from log output; 'logging filter all 1' then re-enables logging in the same log output configuration as before. Some applications provide more specific filters, e.g. to log a given IMSI only. To employ such filters, set 'logging filter all 0' to disable general logging, and then enable a more specific filter instead.

#### Command

```
logging filter all (0|1)
```

#### Parameters

##### logging

Configure logging

##### filter

Filter log messages

##### all

Do you want to log all messages?

##### 0

Only print messages matched by other filters

##### 1

Bypass filter and print all messages

### 1.5.3 logging filter imsi IMSI

#### Command

```
logging filter imsi IMSI
```

#### Parameters

##### logging

Configure logging

##### filter

Filter log messages

##### imsi

Filter log messages by IMSI

##### IMSI

IMSI to be used as filter

---

### 1.5.4 logging level (rll|cc|mm|rr|mncc|pag|msc|mgcp|ho|db|ref|ctrl|smpp|ranap|vlr|iucs...

#### Command

```
logging level (rll|cc|mm|rr|mncc|pag|msc|mgcp|ho|db|ref|ctrl|smpp|ranap|vlr|iucs|bssap| ↵
sgs|ss|lglobal|llapd|linp|lmux|lmi|lmib|lsms|lctrl|lgtp|lstats|lgsup|loap|lss7| ↵
lsccp|lsua|lm3ua|lmgcp|ljibuf|lrspro|lns|lbssgp|lnsdata|lnssignal|liuup|lpfcp|lcsn1 ↵
) (debug|info|notice|error|fatal)
```

#### Parameters

##### logging

Configure logging

##### level

Set the log level for a specified category

##### rll

A-bis Radio Link Layer (RLL)

##### cc

Layer3 Call Control (CC)

##### mm

Layer3 Mobility Management (MM)

##### rr

Layer3 Radio Resource (RR)

##### mncc

MNCC API for Call Control application

##### pag

Paging Subsystem

##### msc

Mobile Switching Center

##### mgcp

Media Gateway Control Protocol

##### ho

Hand-Over

##### db

Database Layer

##### ref

Reference Counting

##### ctrl

Control interface

##### smpp

SMPP interface for external SMS apps

---

ranap  
Radio Access Network Application Part Protocol

vlr  
Visitor Location Register

iucs  
Iu-CS Protocol

bssap  
BSSAP Protocol (A Interface)

sgs  
SGs Interface (SGsAP)

ss  
Supplementary Services

lglobal  
Library-internal global log family

llapd  
LAPD in libosmogsm

linp  
A-bis Input Subsystem

lmux  
A-bis B-Subchannel TRAU Frame Multiplex

lmi  
A-bis Input Driver for Signalling

lmib  
A-bis Input Driver for B-Channels (voice)

lsms  
Layer3 Short Message Service (SMS)

lctrl  
Control Interface

lgtp  
GPRS GTP library

lstats  
Statistics messages and logging

lgsup  
Generic Subscriber Update Protocol

loap  
Osmocom Authentication Protocol

lss7  
libosmo-sigtran Signalling System 7

---

---

lsccp  
libosmo-sigtran SCCP Implementation

lsua  
libosmo-sigtran SCCP User Adaptation

lm3ua  
libosmo-sigtran MTP3 User Adaptation

lmgcp  
libosmo-mgcp Media Gateway Control Protocol

ljibuf  
libosmo-netif Jitter Buffer

lrspro  
Remote SIM protocol

lns  
GPRS NS layer

lbssgp  
GPRS BSSGP layer

lnsdata  
GPRS NS layer data PDU

lnssignal  
GPRS NS layer signal PDU

liuup  
Iu UP layer

lpfcp  
libosmo-pfcp Packet Forwarding Control Protocol

lcsn1  
libosmo-csn1 Concrete Syntax Notation 1 codec

debug  
Log debug messages and higher levels

info  
Log informational messages and higher levels

notice  
Log noticeable messages and higher levels

error  
Log error messages and higher levels

fatal  
Log only fatal messages

---

### 1.5.5 logging level force-all (debug|info|notice|error|fatal)

#### Command

```
logging level force-all (debug|info|notice|error|fatal)
```

#### Parameters

##### logging

Configure logging

##### level

Set the log level for a specified category

##### force-all

Globally force all logging categories to a specific level. This is released by the 'no logging level force-all' command. Note: any 'logging level <category> <level>' commands will have no visible effect after this, until the forced level is released.

##### debug

Log debug messages and higher levels

##### info

Log informational messages and higher levels

##### notice

Log noticeable messages and higher levels

##### error

Log error messages and higher levels

##### fatal

Log only fatal messages

### 1.5.6 logging level set-all (debug|info|notice|error|fatal)

#### Command

```
logging level set-all (debug|info|notice|error|fatal)
```

#### Parameters

##### logging

Configure logging

##### level

Set the log level for a specified category

##### set-all

Once-off set all categories to the given log level. There is no single command to take back these changes -- each category is set to the given level, period.

debug

Log debug messages and higher levels

info

Log informational messages and higher levels

notice

Log noticeable messages and higher levels

error

Log error messages and higher levels

fatal

Log only fatal messages

### 1.5.7 logging print category (0|1)

Command

```
logging print category (0|1)
```

Parameters

logging

Configure logging

print

Log output settings

category

Configure log message

0

Don't prefix each log message

1

Prefix each log message with category/subsystem name

### 1.5.8 logging print category-hex (0|1)

Command

```
logging print category-hex (0|1)
```

Parameters

logging

Configure logging

print

Log output settings

category-hex

Configure log message

0

Don't prefix each log message

1

Prefix each log message with category/subsystem nr in hex ('<000b>')

### 1.5.9 logging print extended-timestamp (0|1)

Command

```
logging print extended-timestamp (0|1)
```

Parameters

logging

Configure logging

print

Log output settings

extended-timestamp

Configure log message timestamping

0

Don't prefix each log message

1

Prefix each log message with current timestamp with YYYYMMDDhhmmssnnn

### 1.5.10 logging print file (0|1|basename) [last]

Command

```
logging print file (0|1|basename) [last]
```

Parameters

logging

Configure logging

print

Log output settings

---

file

Configure log message

0

Don't prefix each log message

1

Prefix each log message with the source file and line

basename

Prefix each log message with the source file's basename (strip leading paths) and line

[last]

Log source file info at the end of a log line. If omitted, log source file info just before the log text.

### 1.5.11 logging print level (0|1)

Command

```
logging print level (0|1)
```

Parameters

logging

Configure logging

print

Log output settings

level

Configure log message

0

Don't prefix each log message

1

Prefix each log message with the log level name

### 1.5.12 logging print thread-id (0|1)

Command

```
logging print thread-id (0|1)
```

Parameters

logging

Configure logging

print

Log output settings

thread-id

Configure log message logging Thread ID

0

Don't prefix each log message

1

Prefix each log message with current Thread ID

### 1.5.13 logging timestamp (0|1)

Command

```
logging timestamp (0|1)
```

Parameters

logging

Configure logging

timestamp

Configure log message timestamping

0

Don't prefix each log message

1

Prefix each log message with current timestamp

### 1.5.14 no logging level force-all

Command

```
no logging level force-all
```

Parameters

no

Negate a command or set its defaults

logging

Configure logging

level

Set the log level for a specified category

force-all

Release any globally forced log level set with 'logging level force-all <level>'

## 1.6 config-stats

### 1.6.1 disable

Command

```
disable
```

Parameters

disable

Disable the reporter

### 1.6.2 enable

Command

```
enable
```

Parameters

enable

Enable the reporter

### 1.6.3 flush-period <0-65535>

Command

```
flush-period <0-65535>
```

Parameters

flush-period

Configure stats sub-system

<0-65535>

Send all stats even if they have not changed (i.e. force the flush) every N-th reporting interval. Set to 0 to disable regular flush (default).

### 1.6.4 level (global|peer|subscriber)

#### Command

```
level (global|peer|subscriber)
```

#### Parameters

##### level

Set the maximum group level

##### global

Report global groups only

##### peer

Report global and network peer related groups

##### subscriber

Report global, peer, and subscriber groups

### 1.6.5 local-ip ADDR

#### Command

```
local-ip ADDR
```

#### Parameters

##### local-ip

Set the IP address to which we bind locally

##### ADDR

IP Address

### 1.6.6 mtu <100-65535>

#### Command

```
mtu <100-65535>
```

#### Parameters

##### mtu

Set the maximum packet size

##### <100-65535>

Size in byte

---

### 1.6.7 no local-ip

#### Command

```
no local-ip
```

#### Parameters

no

Negate a command or set its defaults

local-ip

Set the IP address to which we bind locally

### 1.6.8 no mtu

#### Command

```
no mtu
```

#### Parameters

no

Negate a command or set its defaults

mtu

Set the maximum packet size

### 1.6.9 no prefix

#### Command

```
no prefix
```

#### Parameters

no

Negate a command or set its defaults

prefix

Set the item name prefix

### 1.6.10 prefix PREFIX

#### Command

```
prefix PREFIX
```

#### Parameters

##### prefix

Set the item name prefix

##### PREFIX

The prefix string

### 1.6.11 remote-ip ADDR

#### Command

```
remote-ip ADDR
```

#### Parameters

##### remote-ip

Set the remote IP address to which we connect

##### ADDR

IP Address

### 1.6.12 remote-port <1-65535>

#### Command

```
remote-port <1-65535>
```

#### Parameters

##### remote-port

Set the remote port to which we connect

##### <1-65535>

Remote port number

---

## 1.7 config-line

### 1.7.1 bind A.B.C.D [<0-65535>]

#### Command

```
bind A.B.C.D [<0-65535>]
```

#### Parameters

bind

Accept VTY telnet connections on local interface

A.B.C.D

Local interface IP address (default: 127.0.0.1)

[<0-65535>]

Local TCP port number

### 1.7.2 login

#### Command

```
login
```

#### Parameters

login

Enable password checking

### 1.7.3 no login

#### Command

```
no login
```

#### Parameters

no

Negate a command or set its defaults

login

Enable password checking

## 1.8 config-ctrl

### 1.8.1 bind A.B.C.D

#### Command

```
bind A.B.C.D
```

#### Parameters

##### bind

Set bind address to listen for Control connections

##### A.B.C.D

Local IP address (default 127.0.0.1)

## 1.9 config-cs7

### 1.9.1 as NAME (sua|m3ua|ipa)

#### Command

```
as NAME (sua|m3ua|ipa)
```

#### Global attributes

##### Flag: !

This command applies immediately

#### Parameters

##### as

Configure an Application Server

##### NAME

Name of the Application Server

##### sua

SCCP User Adaptation

##### m3ua

MTP3 User Adaptation

##### ipa

IPA Multiplex (SCCP Lite)

---

### 1.9.2 asp NAME <0-65535> <0-65535> (sua|m3ua|ipa)

#### Command

```
asp NAME <0-65535> <0-65535> (sua|m3ua|ipa)
```

#### Global attributes

Flag: @

This command applies on VTY node exit

#### Parameters

asp

Configure Application Server Process

NAME

Name of ASP

<0-65535>

Remote SCTP port number

<0-65535>

Local SCTP port number

sua

SCCP User Adaptation

m3ua

MTP3 User Adaptation

ipa

IPA Multiplex (SCCP Lite)

### 1.9.3 description .TEXT

#### Command

```
description .TEXT
```

#### Parameters

description

Save human-readable description of the object

.TEXT

Text until the end of the line

### 1.9.4 network-indicator (international | national | reserved | spare)

#### Command

```
network-indicator (international | national | reserved | spare)
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

network-indicator

Configure the Network Indicator

international

International Network

national

National Network

reserved

Reserved Network

spare

Spare Network

### 1.9.5 no as NAME

#### Command

```
no as NAME
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

no

Negate a command or set its defaults

as

Disable Application Server

NAME

Name of AS

### 1.9.6 no asp NAME

#### Command

```
no asp NAME
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

no

Negate a command or set its defaults

asp

Disable Application Server Process

NAME

Name of ASP

### 1.9.7 no sccp-address NAME

#### Command

```
no sccp-address NAME
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

no

Negate a command or set its defaults

sccp-address

Delete an SCCP addressbook entry

NAME

Name of the SCCP Address

### 1.9.8 point-code POINT\_CODE

#### Command

```
point-code POINT_CODE
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

point-code

Configure the local Point Code

POINT\_CODE

Point Code

### 1.9.9 point-code delimiter (default|dash)

#### Command

```
point-code delimiter (default|dash)
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

point-code

Point Code

delimiter

Configure Point Code Delimiter

default

Use dot as delimiter

dash

User dash as delimiter

### 1.9.10 point-code format <1-24> [<1-23>] [<1-22>]

#### Command

```
point-code format <1-24> [<1-23>] [<1-22>]
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

point-code

Point Code

format

Configure Point Code Format

<1-24>

Length of first PC component

[<1-23>]

Length of second PC component

[<1-22>]

Length of third PC component

### 1.9.11 point-code format default

#### Command

```
point-code format default
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

point-code

Point Code

format

Configure Point Code Format

default

Default Point Code Format (3.8.3)

---

### 1.9.12 sccp-address NAME

#### Command

```
sccp-address NAME
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

sccp-address

Create/Modify an SCCP addressbook entry

NAME

Name of the SCCP Address

### 1.9.13 sccp-timer (conn\_est|ias|iar|rel|repeat\_rel|int|guard|reset|reassembly) <1-99999...

#### Command

```
sccp-timer (conn_est|ias|iar|rel|repeat_rel|int|guard|reset|reassembly) <1-99999>
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

sccp-timer

Configure SCCP timer values, see ITU-T Q.714

conn\_est

Waiting for connection confirm message, 1 to 2 minutes (default: 60)

ias

Send keep-alive: on an idle connection, delay before sending an Idle Timer message, 5 to 10 minutes (default: 420)

iar

Receive keep-alive: on an idle connection, delay until considering a connection as stale, 11 to 21 minutes (default: 900)

rel

Waiting for release complete message, 10 to 20 seconds (default: 10)

repeat\_rel

Waiting for release complete message; or to repeat sending released message after the initial expiry, 10 to 20 seconds (default: 10)

**int**

Waiting for release complete message; or to release connection resources, freeze the LRN and alert a maintenance function after the initial expiry, extending to 1 minute (default: 60)

**guard**

Waiting to resume normal procedure for temporary connection sections during the restart procedure, 23 to 25 minutes (default: 1380)

**reset**

Waiting to release temporary connection section or alert maintenance function after reset request message is sent, 10 to 20 seconds (default: 10)

**reassembly**

Waiting to receive all the segments of the remaining segments, single segmented message after receiving the first segment, 10 to 20 seconds (default: 10)

**<1-999999>**

Timer value, in seconds

### 1.9.14 xua rkm routing-key-allocation (static-only|dynamic-permitted)

**Command**

```
xua rkm routing-key-allocation (static-only|dynamic-permitted)
```

**Global attributes****Flag: !**

This command applies immediately

**Parameters****xua**

SIGTRAN xxxUA related

**rkm**

Routing Key Management

**routing-key-allocation**

Routing Key Management Allocation Policy

**static-only**

Only static (pre-configured) Routing Keys permitted

**dynamic-permitted**

Dynamically allocate Routing Keys for what ASPs request

---

## 1.10 config-cs7-as

### 1.10.1 asp NAME

Command

```
asp NAME
```

Global attributes

Flag: !

This command applies immediately

Parameters

asp

Specify that a given ASP is part of this AS

NAME

Name of ASP to be added to AS

### 1.10.2 description .TEXT

Command

```
description .TEXT
```

Parameters

description

Save human-readable description of the object

.TEXT

Text until the end of the line

### 1.10.3 no asp NAME

Command

```
no asp NAME
```

Global attributes

Flag: !

This command applies immediately

#### Parameters

no

Negate a command or set its defaults

asp

Specify ASP to be removed from this AS

NAME

Name of ASP to be removed

### 1.10.4 no traffic-mode

#### Command

```
no traffic-mode
```

#### Parameters

no

Negate a command or set its defaults

traffic-mode

Remove explicit traffic mode of operation of this AS

### 1.10.5 point-code override dpc PC

#### Command

```
point-code override dpc PC
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

point-code

Point Code Specific Features

override

Override (force) a point-code to hard-coded value

dpc

Override Source Point Code

PC

Override Destination Point Code

---

### 1.10.6 point-code override patch-sccp (disabled|both)

#### Command

```
point-code override patch-sccp (disabled|both)
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

point-code

Point Code Specific Features

override

Override (force) a point-code to hard-coded value

patch-sccp

Patch point code values into SCCP called/calling address

disabled

Don't patch any point codes into SCCP called/calling address

both

Patch both origin and destination point codes into SCCP called/calling address

### 1.10.7 qos-class <0-255>

#### Command

```
qos-class <0-255>
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

qos-class

Specity QoS Class of AS

<0-255>

QoS Class of AS

---

### 1.10.8 recovery-timeout <1-2000>

#### Command

```
recovery-timeout <1-2000>
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

recovery-timeout

Specifies the recovery timeout value in milliseconds

<1-2000>

Recovery Timeout in Milliseconds

### 1.10.9 routing-key RCONTEXT DPC

#### Command

```
routing-key RCONTEXT DPC
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

routing-key

Define a routing key

RCONTEXT

Routing context number

DPC

Destination Point Code

### 1.10.10 routing-key RCONTEXT DPC si (aal2|bicc|b-isup|h248|isup|sat-isup|sccp|tup)

#### Command

```
routing-key RCONTEXT DPC si (aal2|bicc|b-isup|h248|isup|sat-isup|sccp|tup)
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

routing-key

Define a routing key

RCONTEXT

Routing context number

DPC

Destination Point Code

si

Match on Service Indicator

aal2

ATM Adaption Layer 2

bicc

Bearer Independent Call Control

b-isup

Broadband ISDN User Part

h248

H.248

isup

ISDN User Part

sat-isup

Sattelite ISDN User Part

sccp

Signalling Connection Control Part

tup

Telephony User Part

---

## 1.10.11 routing-key RCONTEXT DPC si (aal2|bicc|b-isup|h248|isup|sat-isup|sccp|tup) ssn S...

### Command

```
routing-key RCONTEXT DPC si (aal2|bicc|b-isup|h248|isup|sat-isup|sccp|tup) ssn SSN
```

### Global attributes

Flag: !

This command applies immediately

### Parameters

#### routing-key

Define a routing key

#### RCONTEXT

Routing context number

#### DPC

Destination Point Code

#### si

Match on Service Indicator

#### aal2

ATM Adaption Layer 2

#### bicc

Bearer Independent Call Control

#### b-isup

Broadband ISDN User Part

#### h248

H.248

#### isup

ISDN User Part

#### sat-isup

Sattelite ISDN User Part

#### sccp

Signalling Connection Control Part

#### tup

Telephony User Part

#### ssn

Match on Sub-System Number

#### SSN

Sub-System Number to match on

### 1.10.12 routing-key RCONTEXT DPC ssn SSN

#### Command

```
routing-key RCONTEXT DPC ssn SSN
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

##### routing-key

Define a routing key

##### RCONTEXT

Routing context number

##### DPC

Destination Point Code

##### ssn

Match on Sub-System Number

##### SSN

Sub-System Number to match on

### 1.10.13 traffic-mode (broadcast | loadshare | roundrobin | override)

#### Command

```
traffic-mode (broadcast | loadshare | roundrobin | override)
```

#### Parameters

##### traffic-mode

Specifies traffic mode of operation of the ASP within the AS

##### broadcast

Broadcast to all ASP within AS

##### loadshare

Share Load among all ASP within AS

##### roundrobin

Round-Robin between all ASP within AS

##### override

Override

---

## 1.11 config-cs7-asp

### 1.11.1 block

#### Command

```
block
```

#### Global attributes

Flag: @

This command applies on VTY node exit

#### Parameters

block

Allows a SCTP Association with ASP, but doesn't let it become active

### 1.11.2 description .TEXT

#### Command

```
description .TEXT
```

#### Parameters

description

Save human-readable description of the object

.TEXT

Text until the end of the line

### 1.11.3 local-ip (A.B.C.D|X:X::X:X)

#### Command

```
local-ip (A.B.C.D|X:X::X:X)
```

#### Global attributes

Flag: @

This command applies on VTY node exit

#### Parameters

local-ip

Specify Local IP Address from which to contact ASP

A.B.C.D

Local IPv4 Address from which to contact of ASP

X:X::X:X

Local IPv6 Address from which to contact of ASP

### 1.11.4 no quirk (no\_notify|daud\_in\_asp|snm\_inactive)

#### Command

```
no quirk (no_notify|daud_in_asp|snm_inactive)
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

no

Negate a command or set its defaults

quirk

Disable quirk to work around interop issues

no\_notify

Peer SG doesn't send NTFY(AS-INACTIVE) after ASP-UP

daud\_in\_asp

Allow Rx of DAUD in ASP role

snm\_inactive

Allow Rx of [S]SNM in AS-INACTIVE state

### 1.11.5 qos-class <0-255>

#### Command

```
qos-class <0-255>
```

#### Global attributes

Flag: @

This command applies on VTY node exit

#### Parameters

qos-class

Specify QoS Class of ASP

<0-255>

QoS Class of ASP

### 1.11.6 quirk (no\_notify|daud\_in\_asp|snm\_inactive)

#### Command

```
quirk (no_notify|daud_in_asp|snm_inactive)
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

##### quirk

Enable quirk to work around interop issues

##### no\_notify

Peer SG doesn't send NTFY(AS-INACTIVE) after ASP-UP

##### daud\_in\_asp

Allow Rx of DAUD in ASP role

##### snm\_inactive

Allow Rx of [S]SNM in AS-INACTIVE state

### 1.11.7 remote-ip (A.B.C.D|X:X::X:X)

#### Command

```
remote-ip (A.B.C.D|X:X::X:X)
```

#### Global attributes

Flag: @

This command applies on VTY node exit

#### Parameters

##### remote-ip

Specify Remote IP Address of ASP

##### A.B.C.D

Remote IPv4 Address of ASP

##### X:X::X:X

Remote IPv6 Address of ASP

### 1.11.8 role (sg|asp|ipsp)

#### Command

```
role (sg|asp|ipsp)
```

#### Global attributes

Flag: @

This command applies on VTY node exit

#### Parameters

role

Specify the xUA role for this ASP

sg

SG (Signaling Gateway)

asp

ASP (Application Server Process)

ipsp

IPSP (IP Signalling Point)

### 1.11.9 sctp-role (client|server)

#### Command

```
sctp-role (client|server)
```

#### Global attributes

Flag: @

This command applies on VTY node exit

#### Parameters

sctp-role

Specify the SCTP role for this ASP

client

Operate as SCTP client; connect to a server

server

Operate as SCTP server; wait for client connections

### 1.11.10 shutdown

Command

```
shutdown
```

Global attributes

Flag: @

This command applies on VTY node exit

Parameters

shutdown

Terminates SCTP association; New associations will be rejected

## 1.12 config-cs7-sccpaddr

### 1.12.1 global-title

Command

```
global-title
```

Global attributes

Flag: !

This command applies immediately

Parameters

global-title

Add/Modify Global Title

### 1.12.2 no global-title

Command

```
no global-title
```

Global attributes

Flag: !

This command applies immediately

Parameters

no

Negate a command or set its defaults

global-title

Remove Global Title

### 1.12.3 no point-code

#### Command

```
no point-code
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

no

Negate a command or set its defaults

point-code

Remove point-code Number

### 1.12.4 no subsystem-number

#### Command

```
no subsystem-number
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

no

Negate a command or set its defaults

subsystem-number

Remove Subsystem Number

### 1.12.5 point-code POINT\_CODE

#### Command

```
point-code POINT_CODE
```

#### Global attributes

---

Flag: !

This command applies immediately

Parameters

point-code

Add point-code Number

POINT\_CODE

PC

### 1.12.6 routing-indicator (GT|PC|IP)

Command

```
routing-indicator (GT|PC|IP)
```

Global attributes

Flag: !

This command applies immediately

Parameters

routing-indicator

Add Routing Indicator

GT

by global-title

PC

by point-code

IP

by ip-address

### 1.12.7 subsystem-number <0-4294967295>

Command

```
subsystem-number <0-4294967295>
```

Global attributes

Flag: !

This command applies immediately

Parameters

subsystem-number

Add Subsystem Number

<0-4294967295>

SSN

## 1.13 config-cs7-sccpaddr-gt

### 1.13.1 digits DIGITS

#### Command

```
digits DIGITS
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

#### digits

Set Global Title Digits

#### DIGITS

Number digits

### 1.13.2 global-title-indicator <0-15>

#### Command

```
global-title-indicator <0-15>
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

#### global-title-indicator

Set Global Title Indicator

#### <0-15>

GTI

### 1.13.3 nature-of-address-indicator <0-127>

#### Command

```
nature-of-address-indicator <0-127>
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

nature-of-address-indicator

Set Global Title Nature of Address Indicator

<0-127>

NAI

### 1.13.4 numbering-plan-indicator <0-15>

#### Command

```
numbering-plan-indicator <0-15>
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

numbering-plan-indicator

Set Global Title Numbering Plan Indicator

<0-15>

NPI

### 1.13.5 translation-type <0-255>

#### Command

```
translation-type <0-255>
```

#### Global attributes

---

Flag: !

This command applies immediately

Parameters

translation-type

Set Global Title Translation Type

<0-255>

TT

## 1.14 config-cpu-sched

### 1.14.1 cpu-affinity (self|all|<0-4294967295>|THREADNAME) CPUHEXMASK [delay]

Command

```
cpu-affinity (self|all|<0-4294967295>|THREADNAME) CPUHEXMASK [delay]
```

Global attributes

Flag: !

This command applies immediately

Parameters

cpu-affinity

Set CPU affinity mask on a (group of) thread(s)

self

Set CPU affinity mask on thread running the VTY

all

Set CPU affinity mask on all process' threads

<0-4294967295>

Set CPU affinity mask on a thread with specified PID

THREADNAME

Set CPU affinity mask on a thread with specified thread name

CPUHEXMASK

CPU affinity mask

[delay]

If set, delay applying the affinity mask now and let the app handle it at a later point

### 1.14.2 policy rr <1-32>

#### Command

```
policy rr <1-32>
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

##### policy

Set the scheduling policy to use for the process

##### rr

Use the SCHED\_RR real-time scheduling algorithm

##### <1-32>

Set the SCHED\_RR real-time priority

## 1.15 config-net

### 1.15.1 authentication (optional|required)

#### Command

```
authentication (optional|required)
```

#### Parameters

##### authentication

Whether to enforce MS authentication in 2G

##### optional

Allow MS to attach via 2G BSC without authentication

##### required

Always do authentication

### 1.15.2 call-waiting

#### Command

```
call-waiting
```

#### Parameters

##### call-waiting

Enable Call Waiting on the Network

---

### 1.15.3 encryption a5 <0-4> [<0-4>] [<0-4>] [<0-4>] [<0-4>]

#### Command

```
encryption a5 <0-4> [<0-4>] [<0-4>] [<0-4>] [<0-4>]
```

#### Parameters

##### encryption

Encryption options

##### a5

GSM A5 Air Interface Encryption.

##### <0-4>

A5/n Algorithm Number

##### [<0-4>]

A5/n Algorithm Number

##### [<0-4>]

A5/n Algorithm Number

##### [<0-4>]

A5/n Algorithm Number

##### [<0-4>]

A5/n Algorithm Number

### 1.15.4 encryption uea <0-2> [<0-2>] [<0-2>]

#### Command

```
encryption uea <0-2> [<0-2>] [<0-2>]
```

#### Parameters

##### encryption

Encryption options

##### uea

UTRAN (3G) encryption algorithms to allow: 0 = UEA0 (no encryption), 1 = UEA1, 2 = UEA2.

##### <0-2>

UEAn Algorithm Number

##### [<0-2>]

UEAn Algorithm Number

##### [<0-2>]

UEAn Algorithm Number

---

### 1.15.5 long name NAME

#### Command

```
long name NAME
```

#### Parameters

long

Set the long GSM network name

name

Name Commands

NAME

Name to use

### 1.15.6 mgw <0-255>

#### Command

```
mgw <0-255>
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

mgw

Select a MGCP client config to setup

<0-255>

reference number

### 1.15.7 mm info (0|1)

#### Command

```
mm info (0|1)
```

#### Parameters

mm

Mobility Management

info

Send MM INFO after LOC UPD ACCEPT

0

Disable

1

Enable

### 1.15.8 mobile network code <0-999>

#### Command

```
mobile network code <0-999>
```

#### Parameters

##### mobile

Set the GSM mobile network code

##### network

Network Commands

##### code

Code commands

##### <0-999>

Mobile Network Code to use

### 1.15.9 network country code <1-999>

#### Command

```
network country code <1-999>
```

#### Parameters

##### network

Set the GSM network country code

##### country

Country commands

##### code

Code commands

##### <1-999>

Network Country Code to use

### 1.15.10 no call-waiting

#### Command

```
no call-waiting
```

#### Parameters

##### no

Negate a command or set its defaults

##### call-waiting

Disable Call Waiting on the Network

---

### 1.15.11 no mgw <0-255>

#### Command

```
no mgw <0-255>
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

no

Negate a command or set its defaults

mgw

Select a MGCP client config to remove

<0-255>

reference number

### 1.15.12 no timezone

#### Command

```
no timezone
```

#### Parameters

no

Negate a command or set its defaults

timezone

Disable network timezone override, use system tz

### 1.15.13 rrlp mode (none|ms-based|ms-preferred|ass-preferred)

#### Command

```
rrlp mode (none|ms-based|ms-preferred|ass-preferred)
```

#### Parameters

rrlp

Radio Resource Location Protocol

mode

Set the Radio Resource Location Protocol Mode

none

Don't send RRLP request

ms-based

Request MS-based location

ms-preferred

Request any location, prefer MS-based

ass-preferred

Request any location, prefer MS-assisted

### 1.15.14 short name NAME

Command

```
short name NAME
```

Parameters

short

Set the short GSM network name

name

Name Commands

NAME

Name to use

### 1.15.15 timezone <-19-19> (0|15|30|45)

Command

```
timezone <-19-19> (0|15|30|45)
```

Parameters

timezone

Set the Timezone Offset of the network

<-19-19>

Timezone offset (hours)

0

Timezone offset (00 minutes)

15

Timezone offset (15 minutes)

30

Timezone offset (30 minutes)

45

Timezone offset (45 minutes)

## 1.15.16 **timezone** <-19-19> (0|15|30|45) <0-2>

### Command

```
timezone <-19-19> (0|15|30|45) <0-2>
```

### Parameters

#### timezone

Set the Timezone Offset of the network

#### <-19-19>

Timezone offset (hours)

#### 0

Timezone offset (00 minutes)

#### 15

Timezone offset (15 minutes)

#### 30

Timezone offset (30 minutes)

#### 45

Timezone offset (45 minutes)

#### <0-2>

DST offset (hours)

## 1.16 **config-mgw**

### 1.16.1 **description** .TEXT

### Command

```
description .TEXT
```

### Parameters

#### description

Save human-readable description of the object

#### .TEXT

Text until the end of the line

---

### 1.16.2 endpoint-domain NAME

#### Command

```
endpoint-domain NAME
```

#### Parameters

##### endpoint-domain

Set the domain name to send in MGCP messages, e.g. the part 'foo' in 'rtpbridge/\*@foo'.

##### NAME

Domain name, should be alphanumeric.

### 1.16.3 local-ip (A.B.C.D|X:X::X:X)

#### Command

```
local-ip (A.B.C.D|X:X::X:X)
```

#### Parameters

##### local-ip

local bind to connect to MGW from

##### A.B.C.D

local bind IPv4 address

##### X:X::X:X

local bind IPv6 address

### 1.16.4 local-port <0-65535>

#### Command

```
local-port <0-65535>
```

#### Parameters

##### local-port

local port to connect to MGW from

##### <0-65535>

local bind port

---

### 1.16.5 no reset-endpoint NAME

#### Command

```
no reset-endpoint NAME
```

#### Parameters

no

Negate a command or set its defaults

reset-endpoint

remove an endpoint name from the reset-endpoint list, e.g. 'rtpbridge/\*'

NAME

Endpoint name, e.g. 'rtpbridge/\*' or 'ds/e1-0/s-3/su16-4'.

### 1.16.6 remote-ip (A.B.C.D|X:X::X:X)

#### Command

```
remote-ip (A.B.C.D|X:X::X:X)
```

#### Parameters

remote-ip

remote IP address to reach the MGW at

A.B.C.D

remote IPv4 address

X:X::X:X

remote IPv6 address

### 1.16.7 remote-port <0-65535>

#### Command

```
remote-port <0-65535>
```

#### Parameters

remote-port

remote port to reach the MGW at

<0-65535>

remote port

---

## 1.16.8 reset-endpoint NAME

### Command

```
reset-endpoint NAME
```

### Parameters

#### reset-endpoint

Add an endpoint name that should be reset (DLCX) on connect to the reset-endpoint list, e.g. 'rtpbridge/\*'

#### NAME

Endpoint name, e.g. 'rtpbridge/\*' or 'ds/e1-0/s-3/su16-4'.

## 1.17 config-msc

### 1.17.1 asn1 debug (1|0)

### Command

```
asn1 debug (1|0)
```

### Parameters

#### asn1

ASN.1 settings

#### debug

Enable ASN.1 debug messages

#### 1

Log ASN.1 debug messages to stderr

#### 0

Do not log ASN.1 debug messages to stderr

### 1.17.2 asn1 xer-print (1|0)

### Command

```
asn1 xer-print (1|0)
```

### Parameters

#### asn1

ASN.1 settings

#### xer-print

Log human readable representations of all ASN.1 messages to stderr

#### 1

Log XML representation of all ASN.1 messages to stderr

#### 0

Do not log decoded ASN.1 messages to stderr

---

### 1.17.3 assign-tmsi

#### Command

```
assign-tmsi
```

#### Parameters

assign-tmsi

Assign TMSI during Location Updating.

### 1.17.4 auth-tuple-max-reuse-count <-1-2147483647>

#### Command

```
auth-tuple-max-reuse-count <-1-2147483647>
```

#### Parameters

auth-tuple-max-reuse-count

Configure authentication tuple re-use

<-1-2147483647>

0 to use each auth tuple at most once (default), >0 to limit re-use, -1 to re-use infinitely (vulnerable!).

### 1.17.5 auth-tuple-reuse-on-error (0|1)

#### Command

```
auth-tuple-reuse-on-error (0|1)
```

#### Parameters

auth-tuple-reuse-on-error

Configure authentication tuple re-use when HLR is not responsive

0

Never re-use auth tuples beyond auth-tuple-max-reuse-count (default)

1

If the HLR does not deliver new tuples, do re-use already available old ones.

---

### 1.17.6 check-imei-rqd (0|1|early)

#### Command

```
check-imei-rqd (0|1|early)
```

#### Parameters

##### check-imei-rqd

Send each IMEI to the EIR to ask if it is permitted or not. The EIR is implemented as part of OsmoHLR, and can optionally save the IMEI in the HLR.

0

Do not send IMEIs to the EIR

1

Send each IMEI to the EIR

early

Send each IMEI to the EIR, and do it at the start of the location update. This allows the EIR to receive the IMEI, even if the MS would get rejected when the MSC sends the location update request to the HLR.

### 1.17.7 cs7-instance-a <0-15>

#### Command

```
cs7-instance-a <0-15>
```

#### Parameters

##### cs7-instance-a

Set SS7 to be used by the A-Interface.

<0-15>

SS7 instance reference number

### 1.17.8 cs7-instance-iu <0-15>

#### Command

```
cs7-instance-iu <0-15>
```

#### Parameters

##### cs7-instance-iu

Set SS7 to be used by the Iu-Interface.

<0-15>

SS7 instance reference number

---

### 1.17.9 emergency-call route-to-msisdn MSISDN

#### Command

```
emergency-call route-to-msisdn MSISDN
```

#### Parameters

##### emergency-call

Configure Emergency Call Behaviour

##### route-to-msisdn

MSISDN to which Emergency Calls are Dispatched

##### MSISDN

MSISDN (E.164 Phone Number)

### 1.17.10 handover-number range MSISDN\_FIRST MSISDN\_LAST

#### Command

```
handover-number range MSISDN_FIRST MSISDN_LAST
```

#### Parameters

##### handover-number

Configure a range of MSISDN to be assigned to incoming inter-MSC Handovers for call forwarding.

##### range

Configure a handover number range

##### MSISDN\_FIRST

First Handover Number MSISDN

##### MSISDN\_LAST

Last Handover Number MSISDN

### 1.17.11 iu rab-assign-addr-enc (x213|v4raw)

#### Command

```
iu rab-assign-addr-enc (x213|v4raw)
```

#### Parameters

##### iu

Iu interface protocol options

##### rab-assign-addr-enc

Choose RAB Assignment's Transport Layer Address encoding

##### x213

ITU-T X.213 compliant address encoding (default)

##### v4raw

32bit length raw IPv4 address (for ip.access nano3G)

### 1.17.12 lcls-permitted

#### Command

```
lcls-permitted
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

#### lcls-permitted

Globally allow LCLS (Local Call Local Switch) for all calls on this MSC.

### 1.17.13 mncc external MNCC\_SOCKET\_PATH

#### Command

```
mncc external MNCC_SOCKET_PATH
```

#### Parameters

#### mncc

Configure Mobile Network Call Control

#### external

Use external MNCC handler (changes need a program restart)

#### MNCC\_SOCKET\_PATH

File system path to create the MNCC unix domain socket at

### 1.17.14 mncc guard-timeout <0-255>

#### Command

```
mncc guard-timeout <0-255>
```

#### Parameters

#### mncc

Configure Mobile Network Call Control

#### guard-timeout

Set global guard timer for mncc interface activity

#### <0-255>

guard timer value (sec.)

---

### 1.17.15 mncc internal

#### Command

```
mncc internal
```

#### Parameters

##### mncc

Configure Mobile Network Call Control

##### internal

Use internal MNCC handler (default; changes need a program restart)

### 1.17.16 ncss guard-timeout <0-255>

#### Command

```
ncss guard-timeout <0-255>
```

#### Parameters

##### ncss

Configure call independent Supplementary Services

##### guard-timeout

Set guard timer for session activity

##### <0-255>

guard timer value (sec.), or 0 to disable

### 1.17.17 neighbor (a|iu) cgi <0-999> <0-999> <0-65535> <0-65535> (ran-pc|msc-ipa-name) RA...

#### Command

```
neighbor (a|iu) cgi <0-999> <0-999> <0-65535> <0-65535> (ran-pc|msc-ipa-name) ↔  
RAN_PC_OR_MSC_IPA_NAME
```

#### Parameters

##### neighbor

Add Handover target configuration

##### a

Neighbor on GERAN-A

##### iu

Neighbor on UTRAN-Iu

cgi

Handover target cell by Cell-Global Identifier (MCC, MNC, LAC, CI)

<0-999>

MCC

<0-999>

MNC

<0-65535>

LAC

<0-65535>

CI

ran-pc

SCCP point code of RAN peer

msc-ipa-name

GSUP IPA name of target MSC

RAN\_PC\_OR\_MSC\_IPA\_NAME

Point code or MSC IPA name value

### 1.17.18 neighbor (a|iu) lac <0-65535> (ran-pc|msc-ipa-name) RAN\_PC\_OR\_MSC\_IPA\_NAME

Command

```
neighbor (a|iu) lac <0-65535> (ran-pc|msc-ipa-name) RAN_PC_OR_MSC_IPA_NAME
```

Parameters

neighbor

Add Handover target configuration

a

Neighbor on GERAN-A

iu

Neighbor on UTRAN-Iu

lac

Handover target cell by LAC

<0-65535>

LAC

ran-pc

SCCP point code of RAN peer

msc-ipa-name

GSUP IPA name of target MSC

RAN\_PC\_OR\_MSC\_IPA\_NAME

Point code or MSC IPA name value

### 1.17.19 neighbor (a|iu) lac-ci <0-65535> <0-65535> (ran-pc|msc-ipa-name) RAN\_PC\_OR\_MSC\_I...

#### Command

```
neighbor (a|iu) lac-ci <0-65535> <0-65535> (ran-pc|msc-ipa-name) RAN_PC_OR_MSC_IPA_NAME
```

#### Parameters

##### neighbor

Add Handover target configuration

##### a

Neighbor on GERAN-A

##### iu

Neighbor on UTRAN-Iu

##### lac-ci

Handover target cell by LAC and CI

##### <0-65535>

LAC

##### <0-65535>

CI

##### ran-pc

SCCP point code of RAN peer

##### msc-ipa-name

GSUP IPA name of target MSC

##### RAN\_PC\_OR\_MSC\_IPA\_NAME

Point code or MSC IPA name value

### 1.17.20 no assign-tmsi

#### Command

```
no assign-tmsi
```

#### Parameters

##### no

Negate a command or set its defaults

##### assign-tmsi

Assign TMSI during Location Updating.

### 1.17.21 no lcls-permitted

#### Command

```
no lcls-permitted
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

##### no

Negate a command or set its defaults

##### lcls-permitted

Globally disable LCLS (Local Call Local Switch) for all calls on this MSC.

### 1.17.22 no neighbor (a|iu) (ran-pc|msc-ipa-name) RAN\_PC\_OR\_MSC\_IPA\_NAME

#### Command

```
no neighbor (a|iu) (ran-pc|msc-ipa-name) RAN_PC_OR_MSC_IPA_NAME
```

#### Parameters

##### no

Negate a command or set its defaults

##### neighbor

Remove Handover target

##### a

Neighbor on GERAN-A

##### iu

Neighbor on UTRAN-Iu

##### ran-pc

SCCP point code of RAN peer

##### msc-ipa-name

GSUP IPA name of target MSC

##### RAN\_PC\_OR\_MSC\_IPA\_NAME

Point code or MSC IPA name value

---

### 1.17.23 no sms-over-gsup

#### Command

```
no sms-over-gsup
```

#### Parameters

no

Negate a command or set its defaults

sms-over-gsup

Disable routing of SMS messages over GSUP

### 1.17.24 nri add <0-32767> [<0-32767>]

#### Command

```
nri add <0-32767> [<0-32767>]
```

#### Parameters

nri

Mapping of Network Resource Indicators to this MSC, for MSC pooling

add

Add NRI value or range to the NRI mapping for this MSC

<0-32767>

First value of the NRI value range, should not surpass the configured 'nri bitlen'.

[<0-32767>]

Last value of the NRI value range, should not surpass the configured 'nri bitlen' and be larger than the first value; if omitted, apply only the first value.

### 1.17.25 nri bitlen <0-15>

#### Command

```
nri bitlen <0-15>
```

#### Parameters

nri

Mapping of Network Resource Indicators to this MSC, for MSC pooling

bitlen

Set number of NRI bits to place in TMSI identities (always starting just after the most significant octet)

<0-15>

bit count (default: NRI\_BITLEN\_DEFAULT)

---

### 1.17.26 nri del <0-32767> [<0-32767>]

#### Command

```
nri del <0-32767> [<0-32767>]
```

#### Parameters

##### nri

Mapping of Network Resource Indicators to this MSC, for MSC pooling

##### del

Remove NRI value or range from the NRI mapping for this MSC

##### <0-32767>

First value of the NRI value range, should not surpass the configured 'nri bitlen'.

##### [<0-32767>]

Last value of the NRI value range, should not surpass the configured 'nri bitlen' and be larger than the first value; if omitted, apply only the first value.

### 1.17.27 osmux (on|off|only)

#### Command

```
osmux (on|off|only)
```

#### Parameters

##### osmux

RTP multiplexing

##### on

Enable OSMUX

##### off

Disable OSMUX

##### only

Only use OSMUX

### 1.17.28 sms-over-gsup

#### Command

```
sms-over-gsup
```

#### Parameters

##### sms-over-gsup

Enable routing of SMS messages over GSUP

---

### 1.17.29 timer [(vlr|mgw|mncc|sccp|geran|utran|sgs)] [TNNNN] [<0-2147483647>|default]

#### Command

```
timer [(vlr|mgw|mncc|sccp|geran|utran|sgs)] [TNNNN] [<0-2147483647>|default]
```

#### Parameters

##### timer

Configure or show timers

##### [vlr]

VLR (Visitors Location Register)

##### [mgw]

MGW (Media Gateway) interface

##### [mncc]

MNCC (Mobile Network Call Control) interface

##### [sccp]

SCCP (Signalling Connection Control Part)

##### [geran]

GERAN (GSM EDGE Radio Access Network)

##### [utran]

UTRAN (UMTS Terrestrial Radio Access Network)

##### [sgs]

SGs interface towards MME

##### [TNNNN]

T- or X-timer-number -- 3GPP compliant timer number of the format '1234' or 'T1234' or 't1234'; Osmocom-specific timer number of the format: 'X1234' or 'x1234'.

##### [<0-2147483647>]

New timer value

##### [default]

Set to default timer value

## 1.18 config-mncc-int

This node allows to configure the default codecs for the internal call control handling.

### 1.18.1 default-codec tch-f (fr|efr|amr)

#### Command

```
default-codec tch-f (fr|efr|amr)
```

#### Parameters

##### default-codec

Set default codec

##### tch-f

Codec for TCH/F

##### fr

Full-Rate

##### efr

Enhanced Full-Rate

##### amr

Adaptive Multi-Rate

### 1.18.2 default-codec tch-h (hr|amr)

#### Command

```
default-codec tch-h (hr|amr)
```

#### Parameters

##### default-codec

Set default codec

##### tch-h

Codec for TCH/H

##### hr

Half-Rate

##### amr

Adaptive Multi-Rate

## 1.19 config-hlr

### 1.19.1 ipa-name NAME

#### Command

```
ipa-name NAME
```

#### Parameters

##### ipa-name

Set the IPA name of this MSC

##### NAME

A unique name for this MSC. For example: PLMN + redundancy server number: MSC-901-70-0. This name is used for GSUP routing and must be set if more than one MSC is connected to the HLR. The default is 'MSC-00-00-00-00-00-00'.

### 1.19.2 remote-ip A.B.C.D

#### Command

```
remote-ip A.B.C.D
```

#### Parameters

##### remote-ip

Remote GSUP address of the HLR

##### A.B.C.D

Remote GSUP address (default: 127.0.0.1)

### 1.19.3 remote-port <1-65535>

#### Command

```
remote-port <1-65535>
```

#### Parameters

##### remote-port

Remote GSUP port of the HLR

##### <1-65535>

Remote GSUP port (default: MSC\_HLR\_REMOTE\_PORT\_DEFAULT)

---

## 1.20 config-sgs

### 1.20.1 counter (ns7|ns11) <0-255>

#### Command

```
counter (ns7|ns11) <0-255>
```

#### Parameters

##### counter

Configure SGs Counter

##### ns7

Non-EPS alert request retry counter

##### ns11

VLR reset retry counter

##### <0-255>

Counter value

### 1.20.2 local-ip A.B.C.D

#### Command

```
local-ip A.B.C.D
```

#### Parameters

##### local-ip

Set the Local IP Address of the SGs interface

##### A.B.C.D

Local IP Address of the SGs interface

### 1.20.3 local-port <0-65535>

#### Command

```
local-port <0-65535>
```

#### Parameters

##### local-port

Set the local SCTP port of the SGs interface

##### <0-65535>

Local SCTP port of the SGs interface

### 1.20.4 timer (ts5|ts6-2|ts7|ts11|ts14|ts15) <1-120>

#### Command

```
timer (ts5|ts6-2|ts7|ts11|ts14|ts15) <1-120>
```

#### Parameters

##### timer

Configure SGs Timer

##### ts5

Paging procedure guard timer

##### ts6-2

TMSI reallocation guard timer

##### ts7

Non-EPS alert procedure guard timer

##### ts11

VLR reset guard timer

##### ts14

UE fallback procedure timer

##### ts15

MO UE fallback procedure guard timer

##### <1-120>

Time in seconds

### 1.20.5 vlr-name FQDN

#### Command

```
vlr-name FQDN
```

#### Parameters

##### vlr-name

Set the SGs VLR Name as per TS 29.118 9.4.22

##### FQDN

Fully-Qualified Domain Name of this VLR

## 1.21 config-smsc

### 1.21.1 database PATH

#### Command

```
database PATH
```

#### Parameters

##### database

Set the path to the MSC-SMS database file

##### PATH

Relative or absolute file system path to the database file (default is 'sms.db')

### 1.21.2 database delete-delivered (0|1)

#### Command

```
database delete-delivered (0|1)
```

#### Parameters

##### database

SMS Database Configuration

##### delete-delivered

Configure if delivered SMS are deleted from DB

0

Do not delete SMS after delivery

1

Delete SMS after delivery

### 1.21.3 database delete-expired (0|1)

#### Command

```
database delete-expired (0|1)
```

#### Parameters

##### database

SMS Database Configuration

##### delete-expired

Configure if expired SMS are deleted from DB

0

Do not delete SMS after expiration of validity period

1

Delete SMS after expiration of validity period

---

### 1.21.4 queue max-failure <1-500>

#### Command

```
queue max-failure <1-500>
```

#### Parameters

queue

SMS Queue

max-failure

Maximum number of delivery failures before giving up

<1-500>

Amount

### 1.21.5 queue max-pending <1-500>

#### Command

```
queue max-pending <1-500>
```

#### Parameters

queue

SMS Queue

max-pending

SMS to deliver in parallel

<1-500>

Amount

### 1.21.6 validity-period (minimum|default) <1-5256000>

#### Command

```
validity-period (minimum|default) <1-5256000>
```

#### Parameters

validity-period

Configure validity period for SMS

minimum

Minimum SMS validity period in minutes

default

Default SMS validity period in minutes

<1-5256000>

Validity period in minutes

---